```
; 4/11/95
;with stop
;!!!!!!!! note:for z8604 with external EEPROM & RS232 !!!!!!!!!!
;-------------------------------------------------------------------------------
-
;       EQUATE STATEMENTS
;-------------------------------------------------------------------------------
-
XRGRPF          .equ    0f0H            ; expanded reg group F (WDT,SMR,PCON)
XRGRP0          .equ    00H             ; expanded reg group 0 (ports)
S1B39           .equ    00000000b       ; B39 value for S1
S2B39           .equ    00000001b       ; B39 value for S2
S3B39           .equ    00000010b       ; B39 value for S3
S1              .equ    00000100b       ; P32 S1 mask for Z86C04
S2              .equ    00001000b       ; P33 S2 mask for Z86C04
S3              .equ    00000010b       ; P31 S3 mask for Z86C04
smr             .equ    0bH             ; stop mode recovery
csh             .equ    00000100b       ;P22 chip sel hi for 93c46
csl             .equ    11111011b       ;P22 chip sel lo for 93c46
clockh          .equ    00000010b       ;P21 clk hi for 93c46
clockl          .equ    11111101b       ;P21 clk lo for 93c46
doh             .equ    00000001b       ;P20 data out hi for 93c46
dol             .equ    11111110b       ;P20 data out lo for 93c46
csport          .equ    P2              ;chip sel port 93c46
dioport         .equ    P2              ;data i/o port 93c46
clkport         .equ    P2              ;clk port 93c46
;*******************************************************************
;       CONTROL REG AND INITIAL VALUES
;*******************************************************************
;
STACKTOP        .equ    07FH            ; start of the stack
STACKEND        .equ    070H            ; end of the stack
GPR_INIT        .EQU    00H             ; init general purpose reg to 00H
RP_INIT         .EQU    00H             ; init register pointer to 00
IMR_INIT        .EQU    00000000B       ; init intr mask reg (di)
IPR_INIT        .EQU    00001111B       ; init intr priority reg
P01M_INIT       .EQU    00000100B       ; init port 0&1 mode reg
P2M_INIT        .EQU    10010000B       ; init port2 mode
P3M_INIT        .EQU    00000001B       ; init port3 mode
PRE1_INIT       .EQU    00001011B       ; init prescalar 1 reg
T1_INIT         .EQU    250D            ; init counter/timer 1 reg /200
TMR_INIT        .EQU    00000000B       ; init timer mode reg
TMR_START       .EQU    00001100B       ; start timer
P0_INIT         .EQU    00000000B       ; init port0
P2_INIT         .EQU    00000000B       ; init port2
P3_INIT         .EQU    00000000B       ; init port3

SMR_INIT        .EQU    11111010B       ; init SMR reg bit1 hi OTP Lo Emulato
r

PCON_INIT       .EQU    11111110B       ; init Port control reg
;
;*******************************************************************
;       PREDEFINED CONTROL REG
;*******************************************************************
;
;SPL             .equ    255             ; stack pointer
GPR             .equ    254             ; general purpose
;RP      -       .equ    253             ; register pointer
;FLAGS           .equ    252             ; cpu flags
```

```
;IMR             .equ    251             ; interrupt mask reg
;IRQ             .equ    250             ; interrupt request
;IPR             .equ    249             ; interrupt priority
;P01M            .equ    248             ; port 0 mode
;P3M             .equ    247             ; port 3 mode
;P2M             .equ    246             ; port 2 mode
;PRE1            .equ    243             ; prescaler for timer 1
;T1              .equ    242             ; timer 1
;TMR             .equ    241             ; timer mode
;P3              .equ    3               ; port 3
;P2              .equ    2               ; port 2
;
;*******NON-PREDEFINED CONTROL REGISTERS USED WITH REGISTER POINTER******
;
WDTMR           .EQU    r15             ; watch dog timer RP=F0
SMR             .EQU    r11             ; stop mode recovery  RP=F0
PCON            .EQU    r0              ; port control RP=F0
;
;---------------------------------------------------------------------------
;       INTERRUPTS
;---------------------------------------------------------------------------

TIMER_ON_IMR    .equ    00100000b       ; turn on int for timer 1

;---------------------------------------------------------------------------
;       GENERAL PURPOSE REGISTERS
;---------------------------------------------------------------------------

;***************************************************************************
; GENERAL PURPOSE REGISTER GROUP 00H-09H (00h-01H reserved)
;***************************************************************************
REGGRP00        .equ    00H             ;
                .equ    REGGRP00        ; reserved
                .equ    REGGRP00+1      ; reserved
                .equ    REGGRP00+2      ; P2
                .equ    REGGRP00+3      ; P3
X3XTMP          .equ    REGGRP00+4      ; trinary add to itself #
X3XTMP1         .equ    REGGRP00+5      ;
X3XTMP2         .equ    REGGRP00+6      ;
X3XTMP3         .equ    REGGRP00+7      ;
TRCXX           .equ    REGGRP00+8      ; trinary number pointer
TCNTR           .equ    REGGRP00+9      ; trinary counter
X3XABCD         .equ    REGGRP00+10     ; trinary number
X3XABCD1        .equ    REGGRP00+11     ; trinary number
X3XABCD2        .equ    REGGRP00+12     ; trinary number
X3XABCD3        .equ    REGGRP00+13     ; trinary number
LPCNTR          .equ    REGGRP00+14     ; Loop counter
B39             .equ    REGGRP00+15     ; button 1,2,3

;               .equ    r0              ; reserved
;               .equ    r1              ; reserved
;               .equ    r2              ; P2
;               .equ    r3              ; P3
x3xtmp          .equ    r4              ; trinary add to itself #
x3xtmp1         .equ    r5              ;
x3xtmp2         .equ    r6              ;
x3xtmp3         .equ    r7              ;
trcxx           .equ    r8              ; trinary number ptr
tcntr           .equ    r9              ; trinary counter
x3xabcd         .equ    r10             ; trinary number
```

A-2

```
x3xabcd1        .equ    r11             ; trinary number
x3xabcd2        .equ    r12             ; trinary number
x3xabcd3        .equ    r13             ; trinary number
lpcntr          .equ    r14             ; Loop counter
b39             .equ    r15             ; button 1,2,3
;*****************************************************************
; GENERAL PURPOSE REGISTER GROUP 10H-1FH
;*****************************************************************
REGGRP10        .equ    10H             ;
RC10B           .equ    REGGRP10        ; Roll Code 1 LSB
RC11B           .equ    REGGRP10+1      ; Roll Code 1
RC12B           .equ    REGGRP10+2      ; Roll Code 1
RC13B           .equ    REGGRP10+3      ; Roll Code 1 MSB
RC20B           .equ    REGGRP10+4      ; Roll Code 2 LSB
RC21B           .equ    REGGRP10+5      ; Roll Code 2
RC22B           .equ    REGGRP10+6      ; Roll Code 2
RC23B           .equ    REGGRP10+7      ; Roll Code 2 MSB
RC30B           .equ    REGGRP10+8      ; Roll Code 3 LSB
RC31B           .equ    REGGRP10+9      ; Roll Code 3
RC32B           .equ    REGGRP10+10     ; Roll Code 3
RC33B           .equ    REGGRP10+11     ; Roll Code 3 MSB
FRAMEPTR        .equ    REGGRP10+12     ; frame pointer
CODEPTR         .equ    REGGRP10+13     ; code pointer
BITPTR          .equ    REGGRP10+14     ; bit pointer
RCPTR           .equ    REGGRP10+15     ; Rolling Code Reg Pointer

rc10b           .equ    r0              ; Roll Code 1 LSB
rc11b           .equ    r1              ; Roll Code 1
rc12b           .equ    r2              ; Roll Code 1
rc13b           .equ    r3              ; Roll Code 1 MSB
rc20b           .equ    r4              ; Roll Code 2 LSB
rc21b           .equ    r5              ; Roll Code 2
rc22b           .equ    r6              ; Roll Code 2
rc23b           .equ    r7              ; Roll Code 2 MSB
rc30b           .equ    r8              ; Roll Code 3 LSB
rc31b           .equ    r9              ; Roll Code 3
rc32b           .equ    r10             ; Roll Code 3
rc33b           .equ    r11             ; Roll Code 3 MSB
frameptr        .equ    r12             ; frame pointer
codeptr         .equ    r13             ; code pointer
bitptr          .equ    r14             ; bit pointer
rcptr           .equ    r15             ; Rolling Code Reg Pointer
;**********************RS-232 Assignments share REGGRP10***************
rs232do         .equ    r5              ; for RS-232 only
rs232di         .equ    r6
rscommand       .equ    r7
rs232docount    .equ    r8
rs232dicount    .equ    r9
rs232odelay     .equ    r10
rs232idelay     .equ    r11
rs232ccount     .equ    r12
rs232page       .equ    r13
rsccount        .equ    r14
rsstart         .equ    r15

RS232DO         .EQU    REGGRP10+5
RS232DI         .EQU    REGGRP10+6
RSCOMMAND       .EQU    REGGRP10+7
RS232DOCOUNT    .EQU    REGGRP10+8
RS232DICOUNT    .EQU    REGGRP10+9
```

A-3

```
RS232ODELAY     .EQU    REGGRP10+10
RS232IDELAY     .EQU    REGGRP10+11
RS232CCOUNT     .EQU    REGGRP10+12
RS232PAGE       .EQU    REGGRP10+13
RSCCOUNT        .EQU    REGGRP10+14
RSSTART         .EQU    REGGRP10+15

RS232OS         .EQU    00000100B       ;RS232 output bit set
RS232OC         .EQU    11111011B       ;RS232 output bit clear
RS232OP         .EQU    P0              ;RS232 output port
RS232IP         .EQU    P2              ;RS232 input port
RS232IM         .EQU    00010000B       ;RS232 input mask
;*************************************************************************
; GENERAL PURPOSE REGISTER GROUP 20H-2FH
;*************************************************************************
REGGRP20        .equ    20H             ;
TRC0            .equ    REGGRP20        ;Trinary Roll Code REG's LSB
TRC1            .equ    REGGRP20+1      ;Trinary Roll Code REG's
TRC2            .equ    REGGRP20+2      ;Trinary Roll Code REG's
TRC3            .equ    REGGRP20+3      ;Trinary Roll Code REG's
TRC4            .equ    REGGRP20+4      ;Trinary Roll Code REG's
TRC5            .equ    REGGRP20+5      ;Trinary Roll Code REG's
TRC6            .equ    REGGRP20+6      ;Trinary Roll Code REG's
TRC7            .equ    REGGRP20+7      ;Trinary Roll Code REG's
TRC8            .equ    REGGRP20+8      ;Trinary Roll Code REG's
TRC9            .equ    REGGRP20+9      ;Trinary Roll Code REG's
SYNC1           .equ    REGGRP20+10     ;sync pulse frame1
TRC10           .equ    REGGRP20+11     ;Trinary Roll Code REG's
TRC11           .equ    REGGRP20+12     ;Trinary Roll Code REG's
TRC12           .equ    REGGRP20+13     ;Trinary Roll Code REG's
TRC13           .equ    REGGRP20+14     ;Trinary Roll Code REG's
TRC14           .equ    REGGRP20+15     ;Trinary Roll Code REG's

trc0            .equ    r0              ;Trinary Roll Code REG's LSB
trc1            .equ    r1              ;Trinary Roll Code REG's
trc2            .equ    r2              ;Trinary Roll Code REG's
trc3            .equ    r3              ;Trinary Roll Code REG's
trc4            .equ    r4              ;Trinary Roll Code REG's
trc5            .equ    r5              ;Trinary Roll Code REG's
trc6            .equ    r6              ;Trinary Roll Code REG's
trc7            .equ    r7              ;Trinary Roll Code REG's
trc8            .equ    r8              ;Trinary Roll Code REG's
trc9            .equ    r9              ;Trinary Roll Code REG's
sync1           .equ    r10             ;sync pulse frame1
trc10           .equ    r11             ;Trinary Roll Code REG's
trc11           .equ    r12             ;Trinary Roll Code REG's
trc12           .equ    r13             ;Trinary Roll Code REG's
trc13           .equ    r14             ;Trinary Roll Code REG's
trc14           .equ    r15             ;Trinary Roll Code REG's

;*************************************************************************
; GENERAL PURPOSE REGISTER GROUP 30H-39H (3Ah-3FH reserved for stack)
;*************************************************************************
REGGRP30        .equ    30H             ;
TRC15           .equ    REGGRP30        ; Trinary Roll Code REG's
TRC16           .equ    REGGRP30+1      ; Trinary Roll Code REG's
TRC17           .equ    REGGRP30+2      ; Trinary Roll Code REG's
TRC18           .equ    REGGRP30+3      ; Trinary Roll Code REG's MSB
TRC19           .equ    REGGRP30+4      ; sync pulse frame0
SYNC0           .equ    REGGRP30+5      ; sync pulse frame0
```

```
RCMIR0          .equ    REGGRP30+6      ; RC mirrored less LSB
RCMIR1          .equ    REGGRP30+7      ; RC mirrored less
RCMIR2          .equ    REGGRP30+8      ; RC mirrored less
RCMIR3          .equ    REGGRP30+9      ; RC mirrored less MSB


trc15           .equ    r0              ; Trinary Roll Code REG's
trc16           .equ    r1              ; Trinary Roll Code REG's
trc17           .equ    r2              ; Trinary Roll Code REG's
trc18           .equ    r3              ; Trinary Roll Code REG's MSB
trc19           .equ    r4              ; sync pulse frame0
sync0           .equ    r5              ; spare
rcmir0          .equ    r6              ; RC mirrored less LSB
rcmir1          .equ    r7              ; RC mirrored less
rcmir2          .equ    r8              ; RC mirrored less
rcmir3          .equ    r9              ; RC mirrored less MSB
;*****************************************************************
; GENERAL PURPOSE REGISTER GROUP 40H-4FH
;*****************************************************************
REGGRP40        .equ    40H             ;
XMTREG          .equ    REGGRP40        ;
LPCTR           .equ    REGGRP40+1      ;
XR00            .equ    REGGRP40+2      ;
XMTREG1         .equ    REGGRP40+3      ;
ACODEPTR        .equ    REGGRP40+4      ;
MTFLAG          .equ    REGGRP40+5      ;
DIVBY10         .equ    REGGRP40+6      ;
TRCPTR          .equ    REGGRP40+7      ;
TEMPH           .equ    REGGRP40+8      ;ee
TEMPL           .equ    REGGRP40+9      ;ee
TEMP            .equ    REGGRP40+10     ;ee
MTEMPH          .equ    REGGRP40+11     ;memory tem eeprom
MTEMPL          .equ    REGGRP40+12     ;memory tem eeprom
MTEMP           .equ    REGGRP40+13     ;memory tem eerom
SERIAL          .equ    REGGRP40+14     ;serial data to/from eeprom
ADDRESS         .equ    REGGRP40+15     ;eeprom address

xmtreg          .equ    r0              ;
lpctr           .equ    r1              ;
xr00            .equ    r2              ;
xmtreg1         .equ    r3              ;
acodeptr        .equ    r4              ;
mtflag          .equ    r5              ;
divby10         .equ    r6              ;
trcptr          .equ    r7              ;
temph           .equ    r8              ;
templ           .equ    r9              ;
temp            .equ    r10             ;
mtemph          .equ    r11             ;
mtempl          .equ    r12             ;
mtemp           .equ    r13             ;
serial          .equ    r14             ;
address         .equ    r15             ;
;
;*****************************************************************
; GENERAL PURPOSE REGISTER GROUP 50H-5FH
;*****************************************************************
REGGRP50        .equ    50H             ;
ACODE0BM        .equ    REGGRP50        ;
ACODE1BM        .equ    REGGRP50+1      ;
```

A-5

```
ACODE2BM        .equ    REGGRP50+2      ;
ACODE3BM        .equ    REGGRP50+3      ;
ACODE4BM        .equ    REGGRP50+4      ;
ACODE5BM        .equ    REGGRP50+5      ;
ACODE6BM        .equ    REGGRP50+6      ;
ACODE7BM        .equ    REGGRP50+7      ;
ACODE8BM        .equ    REGGRP50+8      ;
ACODE9BM        .equ    REGGRP50+9      ;
ACODE10BM       .equ    REGGRP50+10     ;
ACODE11BM       .equ    REGGRP50+11     ;
ACODE12BM       .equ    REGGRP50+12     ;
ACODE13BM       .equ    REGGRP50+13     ;
ACODE14BM       .equ    REGGRP50+14     ;
ACODE15BM       .equ    REGGRP50+15     ;

acode0bm        .equ    r0              ;
acode1bm        .equ    r1              ;
acode2bm        .equ    r2              ;
acode3bm        .equ    r3              ;
acode4bm        .equ    r4              ;
acode5bm        .equ    r5              ;
acode6bm        .equ    r6              ;
acode7bm        .equ    r7              ;
acode8bm        .equ    r8              ;
acode9bm        .equ    r9              ;
acode10bm       .equ    r10             ;
acode11bm       .equ    r11             ;
acode12bm       .equ    r12             ;
acode13bm       .equ    r13             ;
acode14bm       .equ    r14             ;
acode15bm       .equ    r15             ;
;
;*****************************************************************************
; GENERAL PURPOSE REGISTER GROUP 60H-6FH
;*****************************************************************************
REGGRP60        .equ    60H             ;
ACODE16BM       .equ    REGGRP60        ;
ACODE17BM       .equ    REGGRP60+1      ;
ACODE18BM       .equ    REGGRP60+2      ;
ACODE19BM       .equ    REGGRP60+3      ;
RSFLAG          .equ    REGGRP60+4      ;
XMTFLAG         .equ    REGGRP60+5      ;
AC19            .equ    REGGRP60+6      ;
RCP             .equ    REGGRP60+7      ;
LPCNTRA         .equ    REGGRP60+8      ;
FRMCTRH         .equ    REGGRP60+9      ;
FRMCTRL         .equ    REGGRP60+10     ;
ATMP            .equ    REGGRP60+11     ;acode tmp storage
;acode_h        .equ    REGGRP60+12     ;acode rom pointerh
;acode_l        .equ    REGGRP60+13     ;acode rom pointerl
LPCTR1          .equ    REGGRP60+14     ;counter
APTR            .equ    REGGRP60+15     ;acode ram pointer

acode16bm       .equ    r0              ;
acode17bm       .equ    r1              ;
acode18bm       .equ    r2              ;
acode19bm       .equ    r3              ;
rsflag          .equ    r4              ;
xmtflag         .equ    r5              ;
ac19            .equ    r6              ;
```

A-6

```
rcp             .equ    r7              ;
lpcntra         .equ    r8              ;
frmctrh         .equ    r9              ;
frmctrl         .equ    r10             ;
atmp            .equ    r11             ;acode tmp storage
acode           .equ    rr12            ;acode register pair
acode_h         .equ    r12             ;acode rom pointer h
acode_l         .equ    r13             ;acode rom pointer l
lpctrl          .equ    r14             ;counter
aptr            .equ    r15             ;acode ram pointer
;
;*****************************************************************************
; MACROS
;*****************************************************************************
;
WDT             .macro
                .byte   5fh
                .endm
WDH             .macro
                .byte   4fh
                .endm
FILL            .macro
                .byte   0FFh
                .endm
;
;*****************************************************************************
;*****************************************************************************

;*****                    Interrupt Vector Table                        *****
;*****************************************************************************

;*****************************************************************************
;
                .org    0000H

                .word   000CH           ;IRQ0  P3.2
                .word   000CH           ;IRQ1, P3.3
                .word   000CH           ;IRQ2, P3.1
                .word   000CH           ;IRQ3, S/W generated
                .word   000CH           ;IRQ4, S/W generated
                .word   T1_INT          ;IRQ5,Timer T1
;
;*****************************************************************************
;*****************************************************************************
;****            START (poweron reset or stop mode)                      *****
;*****************************************************************************
;*****************************************************************************
;
                .page
                .org     000CH

start:
START:          di                      ; disable interrupts for init
                WDT                     ; hit WDT
;
;*****************************************************************************
;*              Internal RAM Test and Reset All RAM = ?? mS                  *
;*****************************************************************************
;
INIT:           srp     #XRGRPF         ;no,point to control group use stack
```

A-7

```
                ld      r15,#4          ;r15= pointer (bottom of RAM)
write_again:    clr     @r15            ;write RAM(r5)=0 to memory
                inc     r15
                cp      r15,#7FH        ;top of ram 7F
                jr      ult,write_again
;
;*****************************************************************
;       initialize registers
;*****************************************************************
;
                srp     #REGGRP00       ; set the group
;               ld      SMR,#SMR_INIT   ; set smr reg
;
;*****************************************************************
; STACK INITIALIZATION
;*****************************************************************
;
SETSTACK:
                ld      spl,#STACKTOP           ; set the start of the stack
;
;*****************************************************************
; TIMER INITIALIZATION
;*****************************************************************
;
                ld      pre1,#PRE1_INIT         ; set the prescaler
                ld      t1,#T1_INIT             ; set the counter
                ld      tmr,#TMR_START          ; turn on the timer
;
;*****************************************************************
; PORT INITIALIZATION
;*****************************************************************
                clr     P0              ; set port0 lo
                clr     P2              ; set port2 lo
                clr     P3              ; set port3 lo
                ld      p3m,#P3M_INIT           ; set port 3 mode
                ld      p2m,#P2M_INIT           ; set port 2 mode
                ld      p01m,#P01M_INIT         ; set port 1 mode
;
;*****************************************************************
; INTERRUPT INITIALIZATION
;*****************************************************************
;
SETINTERRUPTS:
                ld      ipr,#IPR_INIT   ; set the priority for timer
;
;*****************************************************************
;       initialize EEPROM by reading it
;*****************************************************************
;
                CALL    READMEMORY      ;settle EE lines
;
;*****************************************************************
; MAIN LOOP     CKBUTTON1
;*****************************************************************
;
CKBUTTON1:      CALL    CKB1
                LD      ACODE19BM,AC19
                LD      RCPTR,RCP
;
```

A-8

```
;*****************************************************************
;       Get Rolling Code From EEPROM
;*****************************************************************
;*****************************************************************
;       EE_ADDRESS 11->RC10B,RC11B,RC12B,RC13B
;       EE_ADDRESS 13->RC20B,RC21B,RC22B,RC23B
;       EE_ADDRESS 15->RC30B,RC31B,RC32B,RC33B
;*****************************************************************
;
INITPTRS:       srp     #REGGRP00
                add     RCPTR,#3        ;TOP OF RC RAM
                CP      RCPTR,#RC13B
                JR      nz,CKRC23
                LD      ADDRESS,#11     ;EE PTR
                JR      GETRCODE
CKRC23:         CP      RCPTR,#RC23B
                JR      nz,APTR15
                LD      ADDRESS,#13
                JR      GETRCODE
APTR15:         LD      ADDRESS,#15
GETRCODE:       LD      lpcntr,#2
GETRCODE1:      CALL    READMEMORY
                LD      @RCPTR,MTEMPH   ;HI BYTE
                DEC     RCPTR
                LD      @RCPTR,MTEMPL   ;LO BYTE
                DEC     RCPTR
                DEC     ADDRESS
                DJNZ    lpcntr,GETRCODE1        ;done?
                INC     RCPTR
;
;*****************************************************************
;       Increment Rolling Code by 3
;*****************************************************************
;
INCRCBY3:       srp     #REGGRP10
                ADD     @rcptr,#3d              ;Add 3 to Rolling Code
                LD      bitptr,#3d
INCRNEXT:       INC     rcptr
                ADC     @rcptr,#0
                DJNZ    bitptr,INCRNEXT
;
;*****************************************************************
;       Store updated Rolling Code in EEPROM
;*****************************************************************
;
                CALL    CKB1            ;SAME BUTTON STILL
                CP      ACODE19BM,AC19  ;PRESSED?
                jp      nz,SCHTOPP

                srp     #REGGRP60
                ADD     ADDRESS,#2      ;START EEPROM ADDRESS
SAVRCODE:       LD      lpcntra,#2
SAVRCODE1:      LD      MTEMPH,@RCPTR   ;hi byte
                DEC     RCPTR
                LD      MTEMPL,@RCPTR   ;lo byte
                CALL    WRITEMEMORY
                DEC     RCPTR
                DEC     ADDRESS
                DJNZ    lpcntra,SAVRCODE1
                INC     RCPTR
```

A-9

```
;
;*****************************************************************************
;       get ACODE0BM-ACODE18BM from eeprom
;*****************************************************************************
;
                srp     #REGGRP40
                ld      address,#9              ;highest eeprom addr
                ld      acodeptr,#ACODE18BM     ;highest acode ram addr
GETACODE:       CALL    READMEMORY
                ld      @acodeptr,mtemph        ;hi byte
                DEC     acodeptr
                CP      acodeptr,#4Fh           ;4fh?  done?
                JR      z,ACODONE
                ld      @acodeptr,mtempl
                DEC     address
                djnz    acodeptr,GETACODE
ACODONE:
;
;*****************************************************************
;       Mirror RCX0,1,2,3 into RCMIR0,1,2,3 and zero MSB
;*****************************************************************
;
MIRROR:         srp     #REGGRP10
                ld      codeptr,#RCMIR3         ;RCMIR3 FIRST
NBYTE:          ld      bitptr,#08d             ; set bit counter to 7
SHIFT:          RL      @rcptr                  ; shift RC into carry
                RRC     @codeptr                ; shift carry into mirror
                DJNZ    bitptr,SHIFT
                CP      codeptr,#RCMIR3         ; if RCMIR3 then
                JR      nz,NOTRC3
                AND     RCMIR3,#01111111b       ; set bit 7 RCMIR3 to 0
NOTRC3:         DEC     codeptr                 ;next rcmir
                INC     rcptr
                CP      codeptr,#35H
                JR      nz,NBYTE

                sub     rcptr,#4
;
;*****************************************************************************
;       Trinary conversion & store in TRC0-TRC19                              *
;*****************************************************************************
;
                srp     #REGGRP00       ;set reg pntr
;
                LD      lpcntr,#36H     ;ZERO OUT TRC PREVIOUS TRINARY #'s
ZAGN:           DEC     lpcntr
                CLR     @lpcntr
                CP      lpcntr,#20H
                JR      nz,ZAGN

                LD      TRCXX,#TRC19
                LD      RCPTR,#20
CALCTRNY:       CP      RCPTR,#01       ;calc trinary number
                JR      z,X3XX1
                CALL    ENTR3
                CP      RCPTR,#02       ;=2?
                JR      z,TRICONVXX
                SUB     RCPTR,#2
                LD      tcntr,RCPTR
                ADD     RCPTR,#2
```

A-10

```
                CALL    ENTR3A
ADDAGN:         CALL    AD3XX           ;add to itself
                CALL    AD3XX
                CALL    XFER
                DJNZ    tcntr,ADDAGN    ;TCNTR=0?
                JR      TRICONVXX
X3XX1:          LD      x3xabcd,#01h
                clr     x3xabcd1
                clr     x3xabcd2
                clr     x3xabcd3

TRICONVXX:
                SBC     RCMIR0,x3xabcd
                SBC     RCMIR1,x3xabcd1
                SBC     RCMIR2,x3xabcd2
                SBC     RCMIR3,x3xabcd3
                JR      C,ADDXXBK
INCTRCXX:       INC     @TRCXX
                JR      TRICONVXX

ADDXXBK:        CCF
                LD      lpcntr,x3xabcd
                ADC     RCMIR0,lpcntr
                LD      lpcntr,x3xabcd1
                ADC     RCMIR1,lpcntr
                LD      lpcntr,x3xabcd2
                ADC     RCMIR2,lpcntr
                LD      lpcntr,x3xabcd3
                ADC     RCMIR3,lpcntr
;
                DEC     RCPTR           ; next lower power of 3
                DEC     TRCXX           ; done with TRC00-TRC19 ?
                CP      TRCXX,#SYNC1    ; sync bit position?
                JR      nz,NXCP
                DEC     TRCXX           ;yes
NXCP:           CP      TRCXX,#1FH      ;no
                JR      nz,CALCTRNY
;
;*****************************************************************
;       Transmit initialization                                  *
;*****************************************************************
;
;
;*****************************
;       initialize RSFLAG    *
;*****************************
;
                tm      RS232IP,#RS232IM        ;DATA IN LO?
                JR      z,disrscall
                ld      RSFLAG,#0FFh            ;set rs232 call enable flag
disrscall:
                srp     #REGGRP40               ;set reg pntr
                LD      SYNC1,#02H              ;INITIALIZE SYNC1
                LD      acodeptr,#ACODE0BM-1    ;initialize
                LD      trcptr,#SYNC0           ;for xmt
                LD      BITPTR,#0ffH
                LD      CODEPTR,#SYNC0
                LD      xmtreg,SYNC0
                LD      FRMCTRH,#02H            ;04H INIT FRAME COUNTER H
                LD      FRMCTRL,#0A0H           ;0BH INIT FRAME COUNTER L
```

A-11

```
                clr     address                 ;address for RS232 xfer
                LD      RS232DOCOUNT,#11D       ;turn off RS232 output
                LD      RS232DICOUNT,#0FFH      ;turn off RS232 input
                                                ;incoming data present
                LD      RSCOMMAND,#0FFH         ;turn off rs232 command
                clr     mtflag                  ;initialize mtflag
;
;*****************************************************************
;       Wait for transmit INT                                    *
;*****************************************************************
;
                LD      IMR,#TIMER_ON_IMR       ;INT Mask enable
LOOP:           EI                              ;enable INT

;**********************RS-232 Routine***********************************
RSDATRDY:       CP      RSCOMMAND,#0FFH ;RS232 DATA IN ?
                JR      Z,XMTMTL
                CP      mtflag,#0
                jr      z,RCVMTH
RCVMTL:         LD      mtempl,RS232DI  ;input mtempl
                ld      RSCOMMAND,#0FFH
                clr     mtflag          ;reset mtflag
                call    WRITEMEMORY     ;write mtempl to EEprom
                call    READMEMORY      ;read mtempl from EEprom
XMTMTH:         ld      RS232DO,mtemph  ;rs232 echo back
                ld      RSSTART,#0FFH   ;mtemph
                clr     RS232DOCOUNT
                ld      XMTFLAG,#0FFh   ;set flag
                inc     address
                cp      address,#16D
                jr      nz,XMTMTL
                clr     address         ;set address to 0
                jr      XMTMTL
RCVMTH:         ld      mtemph,RS232DI  ;mtemph
                ld      RSCOMMAND,#0FFH
                ld      mtflag,#0FFH

XMTMTL:         cp      XMTFLAG,#0FFh   ;ck for xmt first byte
                jr      nz,CKSWS
                cp      RS232DOCOUNT,#11D;test for output done
                jr      nz,CKSWS
                ld      RS232DO,mtempl  ;echo back mtempl
                ld      RSSTART,#0FFH
                clr     XMTFLAG
;*****************************************************************
;
CKSWS:          CP      FRMCTRH,#0      ;FRAME CTR = 0?
                JR      nz,LOOP
                cp      FRMCTRL,#0
                JR      nz,LOOP
SCHTOPP:        STOP
;
;*****************************************************************
;       TIMER 1 INTERRUPT ROUTINE                                *
;*****************************************************************
T1_INT:         CALL    CKB1
                EI                      ;enable interrupt
                CP      RSFLAG,#0FFh    ;RS232 CALL ENABLE FLAG
                JR      nz,BEGINT
```

A-12

```
                call    RS232           ;RS232 I/O
;               push    RP              ;?
;
;***************INT pulse on P26*********************************
;               OR      P2,#01000000B   ;set P26 hi             *
;               NOP                     ;                       *
;               AND     P2,#10111111b   ;set P26 lo             *
;************************************************************
;
;***************FRAME 0 sync pulse on P26*************************
;               CP      LPCNTR,#00H     ;testing frame sync pulse       *
;               JR      nz,NOSYNC       ;testing frame sync pulse       *
;               OR      P2,#01000000B   ;set frame sync pulse hi        *
;               JR      BEGINT          ;                               *
;NOSYNC:        AND     P2,#10111111b   ;set frame sync pulse lo        *
;*****************************************************************
;
BEGINT:         INC     BITPTR          ;next bit
                CP      LPCNTR,#00      ;LPCNTR 0 ?
                JR      nz,NEXT
                CP      BITPTR,#00      ;BITPTR 0 ?
                JR      nz,NEXT
                SUB     FRMCTRL,#1      ;DECREMENT FRAME COUNTER
                SBC     FRMCTRH,#0
NEXT:           CALL    XMT             ;XMT next bit
                CP      LPCTR,#45       ;nibble 45?
                JR      nz,CKBP5
CKBP3:          CP      BITPTR,#1
                JR      z,BP00
                IRET
CKBP5:          CP      BITPTR,#03h
                JR      z,BP00
                IRET
BP00:           LD      BITPTR,#0FFH    ;reset bit pointer
                INC     LPCNTR          ;increment nibble pointer
CK2145:         CP      LPCNTR,#21      ;lpcntr>20?
                JR      mi,CK6790       ;no
LP46:           CP      LPCNTR,#46      ;yes,lpcntr<46
                JR      pl,CK6790
XMR00:          LD      xmtreg,#3       ;yes
                IRET
CK6790:         CP      LPCNTR,#67      ;no
                JR      mi,LP91
                CP      LPCNTR,#91
                JR      mi,XMR00
LP91:           CP      LPCNTR,#91      ;LPCNTR=91?
                JR      z,LPCTR00
LPCTR00RET:
                TM      LPCNTR,#00000001b       ;LPCNTR bit0=0?
                JR      nz,INCACODE
                DEC     trcptr          ;no
                LD      CODEPTR,trcptr
                LD      xmtreg,@CODEPTR
                IRET

INCACODE:       INC     acodeptr        ;yes
                LD      CODEPTR,acodeptr
                LD      xmtreg,@CODEPTR
                IRET
```

A-13

```
LPCTR00:        clr     LPCNTR
                LD      TRCPTR,#SYNC0
                LD      acodeptr,#ACODE0BM-1
                LD      xmtreg,SYNC0
                LD      CODEPTR,#SYNC0
                IRET
;
;*****************************************************************************
;       ADD TRINARY NUMBER TO ITSELF ROUTINE                                  *
;*****************************************************************************
AD3XX:          ADD     x3xabcd,x3xtmp  ;add to itself
                ADC     x3xabcd1,x3xtmp1
                ADC     x3xabcd2,x3xtmp2
                ADC     x3xabcd3,x3xtmp3
                ret
;
XFER:           LD      x3xtmp,x3xabcd
                LD      x3xtmp1,x3xabcd1
                LD      x3xtmp2,x3xabcd2
                LD      x3xtmp3,x3xabcd3
                ret
;
ENTR3:          LD      x3xabcd,#03h
                clr     x3xabcd1
                clr     x3xabcd2
                clr     x3xabcd3
                ret
;
ENTR3A:         LD      x3xtmp,#03h
                clr     x3xtmp1
                clr     x3xtmp2
                clr     x3xtmp3
                ret
;
;*****************************************************************************
;       TRANSMIT  ROUTINE                                                     *
;*****************************************************************************
XMT:            CP      XMTREG,#3               ;BLANK TIME?
                JR      z,SBOLO                 ;yes
                CP      XMTREG,#2               ;force trinary
                JR      ule,XMM
                ld      XMTREG,#2               ;TWO
XMM:            LD      XMTREG1,XMTREG          ;no,get xmt code
                COM     XMTREG1                 ;compliment
                AND     XMTREG1,#00000011b      ;mask 2 LSB
                CP      XMTREG1,BITPTR          ;compare bitptr to xmtreg
                JR      le,SBOHI
SBOLO:          AND     P0,#11111110b           ;set P00 lo
                RET
SBOHI:          OR      P0,#00000001b           ;set P00 hi
                RET
;
;*****************************************************************************
; WRITE WORD TO MEMORY
; ADDRESS IS SET IN REG ADDRESS
; DATA IS IN REG MTEMPH AND MTEMPL
; RETURN ADDRESS IS UNCHANGED
;*****************************************************************************
WRITEMEMORY:
                push    RP              ; SAVE THE RP
```

A-14

```
                srp     #REGGRP40       ; set the register pointer

                call    STARTB          ; output the start bit
                ld      serial,#00110000B       ; set byte to enable write
                call    SERIALOUT               ; output the byte
                and     csport,#csl             ; reset the chip select
                call    STARTB          ; output the start bit
                ld      serial,#01000000B       ; set the byte for write
                or      serial,address          ; or in the address
                call    SERIALOUT               ; output the byte
                ld      serial,mtemph           ; set the first byte to write

                call    SERIALOUT               ; output the byte
                ld      serial,mtempl           ; set the second byte to writ
e
                call    SERIALOUT               ; output the byte
                call    ENDWRITE                ; wait for the ready status
                call    STARTB          ; output the start bit
                clr     serial          ; set byte to disable write
                call    SERIALOUT               ; output the byte
                and     csport,#csl             ; reset the chip select
                pop     RP                      ; reset the RP
                ret

;*********************************************************************
; READ WORD FROM MEMORY
; ADDRESS IS SET IN REG ADDRESS
; DATA IS RETURNED IN REG MTEMPH AND MTEMPL
; ADDRESS IS UNCHANGED
;*********************************************************************
READMEMORY:     CALL    CKB1
                push    RP                      ;
                srp     #REGGRP40       ; set the register pointer

                call    STARTB          ; output the start bit
                ld      serial,#10000000B       ; preamble for read
                or      serial,address          ; or in the address
                call    SERIALOUT               ; output the byte
                call    SERIALIN                ; read the first byte
                ld      mtemph,serial           ; save the value in mtemph
                call    SERIALIN                ; read teh second byte
                ld      mtempl,serial           ; save the value in mtempl
                and     csport,#csl             ; reset the chip select
                pop     RP                      ;
                ret
;
;*********************************************************************
; START BIT FOR SERIAL NONVOL
; ALSO SETS DATA DIRECTION AND AND CS
;*********************************************************************
STARTB:
                ld      P2M,#P2M_INIT   ; set port 2 mode forcing output mode
 data
                and     csport,#csl             ;
                and     clkport,#clockl                 ; start by clearing t
he bits
                and     dioport,#dol            ;
                or      csport,#csh             ; set the chip select
                or      dioport,#doh            ; set the data out high
                or      clkport,#clockh         ; set the clock
```

A-15

```
                and     clkport,#clockl         ; reset the clock low
                and     dioport,#dol            ; set the data low
                ret                             ; return

;*************************************************************************
; END OF CODE WRITE
;*************************************************************************
ENDWRITE:
                ld      P2M,#(P2M_INIT+1)       ; set port 2 mode forcing inp
ut mode data
                and     csport,#csl             ; reset the chip select
                nop                             ; delay
                or      csport,#csh             ; set the chip select
ENDWRITELOOP:   WDT                             ; kick the dog
                cp      LPCNTRA,#1
                jr      nz,EWRLP
                call    CKB1
EWRLP:          ld      temph,dioport           ; read the port
                and     temph,#doh              ; mask
                jr      z,ENDWRITELOOP  ; if the bit is low then loop till we
 are done
                and     csport,#csl             ; reset the chip select
                ld      P2M,#P2M_INIT   ; set port 2 mode forcing output mode
                ret
;
;*************************************************************************
; SERIAL OUT
; OUTPUT THE BYTE IN SERIAL
;*************************************************************************
SERIALOUT:      ld      P2M,#P2M_INIT   ; set port 2 mode forcing output mode
 data
                ld      templ,#8H               ; set the count for eight bit
s
SERIALOUTLOOP:
                rlc     serial                  ; get the bit to output into
the carry
                jr      nc,ZEROOUT              ; output a zero if no carry
ONEOUT:
                or      dioport,#doh            ; set the data out high
                or      clkport,#clockh         ; set the clock high
                and     clkport,#clockl         ; reset the clock low
                and     dioport,#dol            ; reset the data out low
                djnz    templ,SERIALOUTLOOP
                                                ; loop till done
                ret                             ; return
ZEROOUT:
                and     dioport,#dol            ; reset the data out low
                or      clkport,#clockh         ; set the clock high
                and     clkport,#clockl         ; reset the clock low
                and     dioport,#dol            ; reset the data out low
                djnz    templ,SERIALOUTLOOP
                                                ; loop till done
                ret                             ; return
;
;*************************************************************************
; SERIAL IN
; INPUTS A BYTE TO SERIAL
;*************************************************************************
SERIALIN:
                ld      P2M,#(P2M_INIT+1)       ; set port 2 mode forcing inp
```

A-16

```
ut mode data
                ld      templ,#8H               ; set the count for eight bit
s
SERIALINLOOP:
                or      clkport,#clockh         ; set the clock high
                rcf                             ; reset the carry flag
                ld      temph,dioport           ; read the port
                and     temph,#doh              ; mask out the bits
                jr      z,DONTSET
                scf                             ; set the carry flag
DONTSET:
                rlc     serial                  ; get the bit into the byte
                and     clkport,#clockl         ; reset the clock low
                djnz    templ,SERIALINLOOP
                                                ; loop till done
                ret                             ; return

;
;
;-------------------------------------------------------------------------
--
;       RS232 DATA ROUTINES
;-------------------------------------------------------------------------
--
;       enter rs232 start with word to output in rs232do

RS232OSTART:    clr     rsstart                 ; one shot
                ld      rs232odelay,#6d         ; set the time delay to 3. mS
                clr     rs232docount            ; start with the counter at 0
                and     RS232OP,#RS232OC        ; clear the output
                jr      NORSOUT                 ;

RS232:          push    rp                      ; save the rp
                srp     #REGGRP10               ; set the group pointer
                cp      RSSTART,#0FFH           ; test for the start flag
                jr      z,RS232OSTART
RS232OUTPUT:
                cp      rs232docount,#11d       ; test for last
                jr      nz,RS232R
                or      RS232OP,#RS232OS        ; set the output idle
                JR      NORSOUT
RS232R:
                djnz    rs232odelay,NORSOUT             ; cycle count time de
lay
                inc     rs232docount                    ; set the count for t
he next cycle
                scf                                     ; set the carry flag
for stop bits
                rrc     rs232do                         ; get the data into t
he carry
                jr      c,RS232SET                      ; if the bit is high
then set
                and     RS232OP,#RS232OC                ; clear the output
                jr      SETTIME                 ; find the delay time
RS232SET:
                or      RS232OP,#RS232OS                ; set the output
SETTIME:
                ld      rs232odelay,#6d         ; set the data output delay
                tm      rs232docount,#00000001b ; test for odd words
                jr      z,NORSOUT                       ; if even done
```

A-17

```
                ld      rs232odelay,#7d         ; set the delay to 7 for odd
                                                ; this gives 6.5 *.51
2mS

NORSOUT:
RS232INPUT:
                cp      rs232dicount,#0FFH              ; test  mode
                jr      nz,RECEIVING                    ; if receiving then j
ump
                tm      RS232IP,#RS232IM                ; test the incoming d
ata for lo start bit
                jr      nz,NORSIN                       ; if the line is stil
l idle then skip
                clr     rs232dicount                    ; start at 0
                ld      rs232idelay,#3                  ; set the delay to mi
d
RECEIVING:
                djnz    rs232idelay,NORSIN              ; skip till delay is
up
                inc     rs232dicount                    ; bit counter
                cp      rs232dicount,#10d               ; test for last timeo
ut
                jr      z,DIEVEN
                tm      RS232IP,#RS232IM                ; test the incoming d
ata
                rcf                                     ; clear the carry
                jr      z,SKIPSETTING           ; if input bit not set skip s
etting carry
                scf                                     ; set the carry
SKIPSETTING:
                rrc     rs232di                         ; save the data into
the memory
                ld      rs232idelay,#6d                 ; set the delay
                tm      rs232dicount,#00000001b ; test for odd
                jr      z,NORSIN                        ; if even skip
                ld      rs232idelay,#7                  ; set the delay
                jr      NORSIN
DIEVEN:
                ld      rs232dicount,#0FFH              ; turn off the input
till next start
                ld      rscommand,rs232di               ; save the value
                clr     rsccount                        ; clear the counter
NORSIN:
                pop     rp                              ; return the rp
                ret
;**********CKB***********************************************
CKB1:           WDT                             ; HIT WDT
                tcm     P3,#S1                  ;switch 1 pressed?
                jp      nz,CKB2
                clr     AC19            ; ,#S1B39  yes
                ld      RCP,#RC10B              ;set rcptr s1
                RET

CKB2:           tcm     P3,#S2                  ;no, switch 2 pressed?
                jp      nz,CKB3
                ld      AC19,#S2B39     ;yes
                ld      RCP,#RC20B              ;set rcptr s2
                RET

CKB3:           tcm     P3,#S3                  ;no, switch 3 pressed?
```

A-18

```
                jp      nz,HELL
                ld      AC19,#S3B39     ;yes
                ld      RCP,#RC30B                ;set rcptr s3
                RET

HELL:           NOP
;               jr      CKB1
                STOP

;
                FILL
                FILL
                FILL
                FILL
                FILL
                FILL
                FILL
                FILL
                FILL
                FILL
                FILL
                FILL
                FILL
                FILL
                FILL
                FILL
.end
```

A-19

; T0 SET TO 2uS clear each edge if timer extension times out then clear radio
; T1 set to 1uS for 256 uS roll to turn on the interrupts and to generate the 1 mS
;
;

Bit 35	Bit 37	Bit 39	ID_BIT	Type
0	0	Add In	0	Normal CMD
0	1	Add In	1	Touch code
0	2	Add In	2	Security
1	0	Add In	3	IR Protector
1	1	Key ID	4	Wall control
1	2	Key ID	5	Up Down CMD
2	0	Key ID	6	Up Down Stop
2	1	Don't learn	7	Open Door Indicator
2	2	Don't learn	8	Aux Function

;
;
;----------
; NON-VOL MEMORY MAP
;----------
;

00	A1	RA1	RADIOP5
01	A1	RA1	RADIO1P5
02	A2	RC1	COUNTP5
03	A2	RC1	COUNT1P5
04	A3	RA2	
05	A3	RA2	
06	A4	RC2	
07	A4	RC2	
08	A5	RA3	
09	A5	RA3	
0A	A6	RC3	
0B	A6	RC3	
0C	A7	RA4	
0D	A7	RA4	
0E	A8	RC4	
0F	A8	RC4	
10	A9	RA5	
11	A9	RA5	
12	A10	RC5	
13	A10	RC5	
14	A11	RA6	
15	A11	RA6	
16	A12	RC6	
17	A12	RC6	
18	B	RA7	
19	B	RA7	
1A	C	RC7	
1B	C	RC7	
1C	CYCLE COUNTER 1ST 16 BITS		
1D	CYCLE COUNTER 2ND 16 BITS		
1E	VACATION FLAG		
1F	A MEMORY ADDRESS LAST WRITTEN		
	0XXXXXXX	ABC CODES	
	1XXXXXXX	D CODES	

;

```
;
;       20-2F   OPERATION BACK TRACK

;       30-3F   FORCE BACK TRACE
;

;-------------------------------------------------------------------------
;       EQUATE STATEMENTS
;-------------------------------------------------------------------------


check_sum_value     .equ    0A2H
TIMER_0             .equ    10H
TIMER_0_EN          .equ    03H
TIMER_1_EN          .equ    0CH

P01M_INIT           .equ    00000100B       ; set mode p00-p03 out
P2M_INIT            .equ    00100100B
P3M_INIT            .equ    00000011B       ; set port3 p30-p33 ANALOG input
P01S_INIT           .equ    00000000B
P2S_INIT            .equ    00100110B
P3S_INIT            .equ    00000000B

;-------------------------------------------------------------------------
;       PERIODS
;-------------------------------------------------------------------------

MONOPER             .equ    38D             ; MONOSTABLE PERIOD *4mS
RTOPERIOD           .equ    130D            ; period *4mS => min 4* period

;-------------------------------------------------------------------------
;       INTERRUPTS
;-------------------------------------------------------------------------

ALL_ON_IMR          .equ    00111001b       ; turn on  int for radio
RETURN_IMR          .equ    00111001b       ; return on the IMR


;*************************************************************************
; Counter group
;*************************************************************************

CounterGroup        .equ    00              ; counter group
LastM1Match         .equ    05H             ; last match 1 delay location
LastMatch           .equ    06H             ; last matching code address
LoopCount           .equ    07H             ; loop counter
CounterA            .equ    08H             ; counter translation MSB
CounterB            .equ    09H             ;
CounterC            .equ    0AH             ;
CounterD            .equ    0BH             ; counter translation LSB
MirrorA -           .equ    0CH             ; back translation MSB
MirrorB             .equ    0DH             ;
MirrorC             .equ    0EH             ;
MirrorD             .equ    0FH             ; back translation LSB
```

```
loopcount       .equ    r7              ;
countera        .equ    r8              ;
counterb        .equ    r9              ;
counterc        .equ    r10             ;
counterd        .equ    r11             ;
mirrora         .equ    r12             ;
mirrorb         .equ    r13             ;
mirrorc         .equ    r14             ;
mirrord         .equ    r15             ;


;*****************************************************************
; LEARN MODE SWITCHES AND ERASE
;*****************************************************************
LearnModeGroup  .equ    10H
SW_B            .equ    LearnModeGroup      ;
CmdSwitch       .equ    LearnModeGroup+1    ; command switch
LearnDebounce   .equ    LearnModeGroup+2    ; learn switch debouncer
LearnTimer      .equ    LearnModeGroup+3    ; learn timer
SkipRadio       .equ    LearnModeGroup+4    ; flag to skip the radio read
ClearCount      .equ    LearnModeGroup+5    ;
EraseTimer      .equ    LearnModeGroup+6    ; erase timer
BIT13           .equ    LearnModeGroup+7    ;
BIT1P5          .equ    LearnModeGroup+8    ;
ID_B            .equ    LearnModeGroup+9    ;
LASTBIT         .equ    LearnModeGroup+10   ;
PAST_MATCH      .equ    LearnModeGroup+11   ;
Mono            .equ    LearnModeGroup+13   ;
RadioTimeOut    .equ    LearnModeGroup+14   ; radio time out
SwitchSkip      .equ    LearnModeGroup+15   ;

cmdswitch       .equ    r1              ;
learndb         .equ    r2              ;
learnt          .equ    r3              ;
skipradio       .equ    r4              ;
eraset          .equ    r6              ;
rto             .equ    r14             ;
mono            .equ    r13             ;

;*****************************************************************
; LEARN EE GROUP FOR LOOPS ECT
;*****************************************************************
LearnEeGroup    .equ    20H             ;
TempH           .equ    LearnEeGroup    ;
TempL           .equ    LearnEeGroup+1  ;
Temp            .equ    LearnEeGroup+2  ;
COUNT1P5H       .equ    LearnEeGroup+3  ; counter value memory
COUNT1P5L       .equ    LearnEeGroup+4  ; counter value memory
CMP             .equ    LearnEeGroup+5
MTempH          .equ    LearnEeGroup+6  ; memory temp
MTempL          .equ    LearnEeGroup+7  ; memory temp
MTemp           .equ    LearnEeGroup+8  ; memory temp
Serial          .equ    LearnEeGroup+9  ; serial data to and from nonvol memory
Address         .equ    LearnEeGroup+10 ; address for the serial nonvol memory
T0Ext           .equ    LearnEeGroup+11 ; timer 0 extend dec every T0 int
T4MS            .equ    LearnEeGroup+12 ; 4 mS counter
```

```
T125MS          .equ    LearnEeGroup+13     ; 125mS counter
COUNTP5H        .equ    LearnEeGroup+14     ; counter value memory
COUNTP5L        .equ    LearnEeGroup+15     ; counter value memory

temph           .equ    r0                  ;
templ           .equ    r1                  ;
temp            .equ    r2                  ;
cmp             .equ    r5                  ;
mtemph          .equ    r6                  ; memory temp
mtempl          .equ    r7                  ; memory temp
mtemp           .equ    r8                  ; memory temp
serial          .equ    r9                  ; serial data to and from nonvol memory
address         .equ    r10                 ; address for the serial nonvol memory
t0ext           .equ    r11                 ; timer 0 extend dec every T0 int
t4ms            .equ    r12                 ; 4 mS counter
t125ms          .equ    r13                 ; 125mS counter


;*****************************************************************
; RADIO GROUP
;*****************************************************************
RadioGroup      .equ    30H                 ;
RTemp           .equ    RadioGroup          ; radio temp storage
RTempH          .equ    RadioGroup+1        ; radio temp storage high
RTempL          .equ    RadioGroup+2        ; radio temp storage low
RTimeAH         .equ    RadioGroup+3        ; radio active time high byte
RTimeAL         .equ    RadioGroup+4        ; radio active time low byte
RTimeIH         .equ    RadioGroup+5        ; radio inactive time high byte
RTimeIL         .equ    RadioGroup+6        ; radio inactive time low byte
RadioP5H        .equ    RadioGroup+7        ; .5 code storage
RadioP5L        .equ    RadioGroup+8        ; .5 code storage
PointerH        .equ    RadioGroup+9        ;
PointerL        .equ    RadioGroup+10       ;
AddValueH       .equ    RadioGroup+11       ;
AddValueL       .equ    RadioGroup+12       ;
RadioC          .equ    RadioGroup+13       ; radio word count
Radio1P5H       .equ    RadioGroup+14       ; 1.5 code storage
Radio1P5L       .equ    RadioGroup+15       ; 1.5 code storage
rtemp           .equ    r0                  ; radio temp storage
rtemph          .equ    r1                  ; radio temp storage high
rtempl          .equ    r2                  ; radio temp storage low
rtimeah         .equ    r3                  ; radio active time high byte
rtimeal         .equ    r4                  ; radio active time low byte
rtimeih         .equ    r5                  ; radio inactive time high byte
rtimeil         .equ    r6                  ; radio inactive time low byte
radiop5h        .equ    r7                  ; radio .5 code storage
radiop5l        .equ    r8                  ; radio .5 code storage
pointerh        .equ    r9                  ;
pointerl        .equ    r10                 ;
addvalueh       .equ    r11                 ;
addvaluel       .equ    r12                 ;
radioc          .equ    r13                 ; radio word count
radio1p5h       .equ    r14                 ; radio 1.5 code storage
radio1p5l       .equ    r15                 ; radio 1.5 code storage
```

```
;*****************************************************************
; Check sum group with past radio data
;*****************************************************************

CheckGroup      .equ    40H
check_sum       .equ    r0              ; check sum pointer
rom_data        .equ    r1
test_adr_hi     .equ    r2
test_adr_lo     .equ    r3
rflag           .equ    r4
test_adr        .equ    rr2
pradioa         .equ    r6
pradiob         .equ    r7
pradioc         .equ    r8
pradiod         .equ    r9
pradioe         .equ    r10
pradiof         .equ    r11
pradiog         .equ    r12
pradioh         .equ    r13

Check_Sum       .equ    CheckGroup+0    ; check sum reg for por
Rom_Data        .equ    CheckGroup+1    ; data read
RFlag           .equ    CheckGroup+4    ; radio flags
RInFilter       .equ    CheckGroup+5    ; radio input filter
PRadioA         .equ    CheckGroup+6    ; past recieved value
PRadioB         .equ    CheckGroup+7    ; past recieved value
PRadioC         .equ    CheckGroup+8    ; past recieved value
PRadioD         .equ    CheckGroup+9    ; past recieved value
PRadioE         .equ    CheckGroup+0AH  ; past recieved value
PRadioF         .equ    CheckGroup+0BH  ; past recieved value
PRadioG         .equ    CheckGroup+0CH  ; past recieved value
PRadioH         .equ    CheckGroup+0DH  ; past recieved value

;*****************************************************************
; Timer group with rs232 data
;*****************************************************************

TimerGroup      .equ    50H
rs232do         .equ    r5
rs232di         .equ    r6
rscommand       .equ    r7
rs232docount    .equ    r8
rs232dicount    .equ    r9
rs232odelay     .equ    r10
rs232idelay     .equ    r11
rs232ccount     .equ    r12
rs232page       .equ    r13
rsccount        .equ    r14
rsstart         .equ    r15

RADIO_CMD       .equ    TimerGroup+0H   ; radio command
TaskSwitch      .equ    TimerGroup+2H
SysDisable      .equ    TimerGroup+3H   ; system disable timer
ADD2            .equ    TimerGroup+4H   ;
```

```
RS232DO         .equ    TimerGroup+5
RS232DI         .equ    TimerGroup+6
RSCommand       .equ    TimerGroup+7
RS232DoCount    .equ    TimerGroup+8
RS232DiCount    .equ    TimerGroup+9
RS232ODelay     .equ    TimerGroup+10
RS232IDelay     .equ    TimerGroup+11
RS232CCount     .equ    TimerGroup+12
RS232Page       .equ    TimerGroup+13
RSCount         .equ    TimerGroup+14       ; rs232 byte counter
RSStart         .equ    TimerGroup+15       ; rs232 start flag
TestVal         .equ    TimerGroup+16       ; test value

STACKTOP        .equ    127D                ; start of the stack
STACKEND        .equ    060H                ; end of the stack


RS232OS         .equ    00000100B           ; RS232 output bit set
RS232OC         .equ    11111011B           ; RS232 output bit clear
RS232OP         .equ    P0                  ; RS232 output port
RS232IP         .equ    P3                  ; RS232 input port
RS232IM         .equ    00000010B           ; RS232 mask
csh             .equ    00000001B           ; chip select high for the 93c46
csl             .equ    11111110B           ; chip select low for 93c46
clockh          .equ    00000010B           ; clock high for 93c46
clockl          .equ    11111101B           ; clock low for 93c46
doh             .equ    00000001B           ; data out high for 93c46
dol             .equ    11111110B           ; data out low for 93c46
csport          .equ    P0                  ; chip select port
dioport         .equ    P2                  ; data i/o port
clkport         .equ    P0                  ; clock port


WDT             .macro
                .byte   5fh
                .endm
WDH             .macro
                .byte   4fh
                .endm
Fill            .macro
                .byte   0FFH
                .endm

;*****************************************************************************
;*
;*              Interrupt Vector Table
;*
;*****************************************************************************

        .org    0000H

                .word   RadioNegInt         ;IRQ0  P3.2 n
                .word   000CH               ;IRQ1, P3.3
                .word   000CH               ;IRQ2, P3.1
```

```
                .word   RadioPosInt             ;IRQ3, P3.2 p FOR EMULATION
                                                ; USE P3.0 FROM 28 PIN
                .word   TimerZeroInt            ;IRQ4, T0
                .word   TimerOneInt             ;IRQ5, T1

                .page
        .org    000CH

;*****************************************************************
; WATCHDOG INITILIZATION
;*****************************************************************
start:
START:  di                                      ; turn off the interrupt for init
        WDH
        WDT                                     ; kick the dog

;*****************************************************************
;*      Internal RAM Test and Reset All RAM =   mS      *
;*****************************************************************
        srp     #0F0h                           ; point to control group use stack
        ld      r15,#4                          ;r15= pointer (minimum of RAM)
write_again:
        WDT                                     ; KICK THE DOG
        ld      r14,#1
write_again1:
        ld      @r15,r14                        ;write 1,2,4,8,10,20,40,80
        cp      r14,@r15                        ;then compare
        jr      ne,system_error
        rl      r14
        jr      nc,write_again1
        clr     @r15                            ;write RAM(r5)=0 to memory
        inc     r15
        cp      r15,#7FH
        jr      ult,write_again


;*****************************************************************
;*              Checksum Test                                    *
;*****************************************************************
CheckSumTest:
        srp     #CheckGroup
        ld      test_adr_hi,#07H
        ld      test_adr_lo,#0FFH               ;maximum address=fffh
add_sum:
        WDT                                     ; KICK THE DOG
        ldc     rom_data,@test_adr              ;read ROM code one by one
        add     check_sum,rom_data              ;add it to checksum register
        decw    test_adr                        ;increment ROM address
        jr      nz,add_sum                      ;address=0 ?
        cp      check_sum,#check_sum_value
;       jr      system_ok
        jr      z,system_ok                     ;check final checksum = 00 ?
system_error:
        and     P2,#11011101B                   ; turn on the LED to indicate fault
```

```
                ld      P2M,#P2M_INIT           ; turn on the LED to indicate fault

                jr      system_error

                .byte   256-check_sum_value
system_ok:

                WDT                             ; kick the dog

                srp     #LearnModeGroup         ; set the group

                ld      eraset,#0FFH            ; set the erase timer
                ld      CmdSwitch,#0FFH         ; set the switch debouncer
                ld      learnt,#0FFH            ; set the learn timer
                ld      learndb,#0FFh           ; set the learn debounce
                ld      RSCommand,#0FFH         ; turn off the rs232 command
                ld      RS232DoCount,#11D       ; turn off the rs232 output


;*****************************************************************************
; STACK INITILIZATION
;*****************************************************************************
SetStack:

                clr     254
                ld      255,#STACKTOP           ; set the start of the stack


;*****************************************************************************
; TIMER INITILIZATION
;*****************************************************************************

                ld      PRE0,#00001001B         ; set the prescaler to / 2 for 8Mhz
                ld      PRE1,#00000111B         ; set the prescaler to / 1 for 8Mhz
                clr     T0                      ; set the counter to count FF through 0
                clr     T1                      ; set the counter to count FF through 0
                ld      TMR,#00001111B          ; turn on the timers and load

;*****************************************************************************
; PORT INITILIZATION
;*****************************************************************************

                ld      P0,#P01S_INIT           ; RESET all ports
                ld      P2,#P2S_INIT            ;
                ld      P3,#P3S_INIT            ;
                ld      P01M,#P01M_INIT         ; set mode
                ld      P3M,#P3M_INIT           ; set port3 p30-p33 input analog mode
                ld      P2M,#P2M_INIT+1         ; set port 2 mode

;*****************************************************************************
; MEMORY INITILIZATION
;*****************************************************************************

                ld      Address,#3EH            ; set non vol address to UNUSED
                call    ReadMemory              ; read the value to INIT
```

```
;*****************************************************************
; INITERRUPT INITILIZATION
;*****************************************************************
SetInterrupts:
            ld      IPR,#00000001B          ; set the priority to timer
            ld      IMR,#ALL_ON_IMR         ; turn on the interrupt
            clr     IRQ                     ; CLEAR IRQ'S

;*****************************************************************
; MAIN LOOP
;*****************************************************************
MainLoop:
            ei                              ; enable interrupt
            and     P2,#01111111b           ; turn off the flag
            WDT                             ; kick the dog
            ld      P01M,#P01M_INIT         ; set mode
            ld      P3M,#P3M_INIT           ; set port3 p30-p33 input analog mode
            ld      P2M,#P2M_INIT+1         ; set port 2 mode

            call    LEARN                   ; do the learn switch
TestRS232:
            srp     #TimerGroup             ;
            cp      rsstart,#0FFH           ; test for starting a transmission
            jr      z,skiprs232             ; if starting a trans skip
            cp      rscommand,#0FFH         ; test for the off mode
            jr      z,skiprs232
            cp      rs232docount,#11d       ; test for output done
            jr      nz,skiprs232            ; if not the skip
;           cp      rscommand,#30H          ; test for switch data
;           jr      nz,TEST34
;           clr     rs232do                 ; clear the data
;
;           cp      LearnDebounce,#0FFH     ; test switch one
;           jr      nz,SW1OUT
;           or      rs232do,#00000001B      ; set the marking bit
;SW1OUT:
;           cp      CmdSwitch,#0FFH         ; test switch 2
;           jr      nz,SW2OUT               ;
;           or      rs232do,#00000010B      ; set the marking bit
;SW2OUT:
;           cp      LearnTimer,#0FFH        ; test for learn 1
;           jr      nz,L1OUT
;           or      rs232do,#00001000B      ; set the marking bit
;L1OUT:
;
;           jr      VacSwOpen               ;
TEST34:
            cp      rscommand,#34H          ; test for page 0
            jr      nz,TEST35
            ld      rs232page,#00H          ;
            jr      RS232PageOUT
TEST35:
            cp      rscommand,#35H          ; test for page 1
            jr      nz,TEST38
```

```
                ld      rs232page,#10H          ;

RS232PageOUT:
                ld      SkipRadio,#0FFH         ; set the skip radio flag
                dec     SwitchSkip              ; turn off the switch testing for port
                                                ; direction control
                ld      Address,rsccount        ; find the address
                rcf                             ;
                rrc     Address                 ;
                or      Address,rs232page       ;
                call    ReadMemory              ; read the data
                ld      rs232do,MTempH
                tm      rsccount,#01H           ; test which byte
                jr      z,RPBYTE
                ld      rs232do,MTempL
RPBYTE:
                cp      rsccount,#1FH           ; test for the end
                jp      nz,STARTOUT
LASTRPM:        clr     rsccount                ; reset the counter
VacSwOpen:
                dec     rsstart                 ; set the start flag
                ld      rscommand,#0FFH         ; turn off command
                                                ; return
skiprs232:
                jp      SKIPRS232

TEST38:
                cp      rscommand,#38H          ; test memory
                jr      nz,SKIPRS232
                ld      rs232do,#0FFH           ; flag set to error to start
                srp     #LearnEeGroup
                dec     SwitchSkip              ; skip testing the switches
                ld      SkipRadio,#0FFH         ; set the skip radio flag
                ld      mtemph,#0FFH            ; set the data to write
                call    WRITEALL                ; write all the words
                call    TESTALL                 ; test all memory
                ld      mtemph,#000H            ; set the data to write
                call    WRITEALL                ; write all memory
                call    TESTALL                 ; test for the data retension
CLEARALL:
                call    CLEARCODES              ; reset the memory for code
                clr     RS232DO                 ; flag all ok
MEMORYERROR:
                ld      RSCommand,#0FFH         ; turn off command
STARTOUT:
                inc     rsccount                ; set to the next address
                dec     RSStart                 ; set the start flag

SKIPRS232:
                clr     SwitchSkip              ; clear the skip switches flag
                clr     SkipRadio               ; clear the skip radio flag

                srp     #LearnModeGroup         ;

SINGLE:
                cp      mono,#MONOPER           ; test for the period
```

```
                jr      ult,TESTCONS            ; if not then test constant output
                and     P2,#11110111b           ; clear the output
                ld      mono,#0FFH              ;
TESTCONS:
                di
                cp      rto,#RTOPERIOD          ; test for the timeout
                jr      ult,SIGDONE
TurnOffOutput:
                and     P2,#11101111b           ; clear the output
                ld      rto,#0FFH
SIGDONE:
TOGGLE:
                jp      MainLoop                ; loop forever


WRITEALL:
                ld      mtempl,mtemph           ;
                ld      TestVal,mtemph          ;
                clr     address                 ; start at address 00
WRITELOOP1:
                WDT
                call    WRITEMEMORY             ;
                inc     address                 ; do the next address
                cp      address,#40H            ; test for the last address
                jr      nz,WRITELOOP1
                ret

TESTALL:
                clr     address                 ; start at address 0
READLOOP1:
                WDT
                call    ReadMemory              ; read the data
                cp      mtemph,TestVal          ; test the value
                jp      nz,MEMORYERROR          ; if error mark
                cp      mtempl,TestVal          ; test the value
                jp      nz,MEMORYERROR          ; if error mark
                inc     address                 ; set the next address
                cp      address,#40H            ; test for the last address
                jr      nz,READLOOP1            ;
                ret


;*****************************************************************************
; Timer 0 interrupt
;*****************************************************************************
TimerZeroInt:
                cp      T0Ext,#00               ; test for the roll
                jr      z,ClearRadioTimeout     ; if at the roll time out
                dec     T0Ext                   ; decrement the time extension
                iret
ClearRadioTimeout:
                call    ClearCounter            ; clear the counter
                push    RP                      ; for the Clear radio code segment
                jp      ClearRadio              ; clear the radio data
```

```
;*****************************************************************
; Radio interrupt from a edge of the radio signal
;*****************************************************************

RadioNegInt:
            and     IMR,#11111110b          ; turn off the interrupt for 256uS
            ld      RTemp,#00000001B        ; mark which edge
            jr      RadioEdge
RadioPosInt:
            and     IMR,#11110111b          ; turn off the interrupt for 256uS
            ld      RTemp,#00000000B        ; mark which edge
            jr      RadioEdge


RadioEdge:

            push    RP                      ; save the reg pair
            srp     #RadioGroup             ; set the register pointer
            ld      rtemph,T0Ext            ; read the upper byte
            ld      rtempl,T0               ; read the lower byte
            tm      IRQ,#00010000b          ; test for a pending timer interrupt
            jr      z,RIncDone              ; done
            tm      rtempl,#10000000b       ; test for the rollover
            jr      z,RIncDone              ; if not the rolled value skip inc
            dec     rtemph                  ; increase the timer msb
RIncDone:
            call    ClearCounter            ; clear the counter
RTimeOk:
            com     rtemph                  ; flip to find the period
            com     rtempl                  ;
RTimeDone:
            cp      rtemp,#0                ; test the port for the edge
            jr      z,ActiveTime            ; if it was the active time then branch
InActiveTime:
            cp      RInFilter,#0FFH         ; test for active last time
            jr      z,GoInActive            ; if so continue
            jr      RADIO_EXIT              ; if not the return
GoInActive:
            clr     RInFilter               ; set flag to inactive
            ld      rtimeih,rtemph          ; transfer the period to inactive
            ld      rtimeil,rtempl          ;
            jr      RADIO_EXIT              ; return
ClearCounter:
            ld      TMR,#00001000b          ; turn off timer 0
            ld      TMR,#00001001b          ; load t0
            ld      TMR,#00001000b          ;
            ld      TMR,#00001010b          ; restart the timer
            ld      T0Ext,#0FFH             ; reset the timer
            and     IRQ,#11100110b          ; turn off pending int
            ret

ActiveTime:
            cp      RInFilter,#00H          ; test for active last time
            jr      z,GoActive              ; if so continue
            jr      RADIO_EXIT              ; if not the return
GoActive:
```

```
                ld      RInFilter,#0FFH         ;
                ld      rtimeah,rtemph          ; transfer the period to active
                ld      rtimeal,rtempl          ;
GotBothEdges:
                ei                              ; enable the interrupts
                cp      radioc,#0               ; test for the blank timing
                jr      nz,INSIG                ; if not then in the middle of signal
                inc     radioc                  ; set the counter to the next number
                cp      rtimeih,#30h            ; test for the min 24.5 mS
                jr      ult,ClearJump           ; if not then clear the radio
                cp      rtimeah,#00h            ; test first the min sync
                jr      nz,SyncOk               ; first byte 00 if not great enough
                cp      rtimeal,#80H            ; test for 256uS min
                jr      ult,ClearJump           ; if less then clear the radio
SyncOk:
                cp      rtimeah,#9h             ; test for the max time 4.6mS
                jr      uge,ClearJump           ; if not clear


SETP5:
                cp      rtimeah,#02h            ; test for 1.5 vs .5
                jr      uge,O1P5MSFLAG          ; set the 1.5 flag
P5MSFLAG:
                or      RFlag,#01000000b        ; set the 0.5ms memory flag
                clr     radiop5h                ; clear the memory
                clr     radiop5l                ;
                clr     COUNTP5H                ; clear the memory
                clr     COUNTP5L                ;
                jr      DONESETP5               ; do the 2X
O1P5MSFLAG:
                and     RFlag,#10111111b        ; set the 1.5ms memory flag
                clr     radio1p5h               ; clear the memory
                clr     radio1p5l               ;
                clr     COUNT1P5H               ; clear the memory
                clr     COUNT1P5L               ;
DONESETP5:
RADIO_EXIT:
                pop     rp
                iret                            ; done return

ClearJump:
;               or      P2,#10000000b           ; turn of the flag bit for clear radio
                jp      ClearRadio              ; clear the radio signal

INSIG:
                cp      rtimeih,#0AH            ; test for the max width 5.16
                jr      uge,ClearJump           ; if too wide clear
                cp      rtimeih,#00h            ; test for the min width
                jr      nz,ISigOk               ; if greater then 0 then signal ok
                cp      rtimeil,#080h           ; test for 256us min
                jr      ult,ClearJump           ; if not then clear the radio
ISigOk:
                cp      rtimeah,#0AH            ; test for the max width
                jr      uge,ClearJump           ; if too wide clear
                cp      rtimeah,#00h            ; if greater then 0 then signal ok
```

```
                jr      nz,ASigOk               ; if too narrow clear
                cp      rtimeal,#080h           ; test for 256us min
                jr      ult,ClearJump           ; if not then clear the radio
ASigOk:
                sub     rtimeal,RTimeIL         ; find the difference
                sbc     rtimeah,rtimeih
                tm      rtimeah,#10000000b      ; find out if neg
                jr      nz,NEGDIFF2             ; use 1 for ABC or D
                jr      POSDIFF2
POSDIFF2:
                cp      rtimeah;#01H            ; test for 1.5/1
                jr      ult,O1PMS               ; mark as a 1
                jr      O1P5MS

NEGDIFF2:
                com     rtimeah                 ; invert
                cp      rtimeah,#01H            ; test for 1/.5
                jr      ult,O1PMSC              ; mark as a .5
                jr      P5MSC
O1P5MS:
                ld      BIT1P5,#2h              ; set the value
                jr      GOTB1P5
O1PMSC:
                com     rtimeah                 ; invert
O1PMS:
                ld      BIT1P5,#1h              ; set the value
                jr      GOTB1P5
P5MSC:
                com     rtimeah                 ; invert
                ld      BIT1P5,#0h              ; set the value
GOTB1P5:
                clr     rtimeah                 ; clear the time
                clr     rtimeal
                clr     rtimeih
                clr     rtimeil
                ei                              ; enable interrupts
ADDB1P5:
                tm      RFlag,#01000000b        ; test for radio p5/ 1p5
                jr      nz,RCP5INC              ;

RC1P5INC:
                tm      radioc,#00000001b       ; test for even odd number
                jr      z,COUNT1P5INC           ; if odd number counter

Radio1P5INC:                                    ; else radio

                cp      radioc,#15D             ; test the radio counter for the specials
                jr      uge,SPECIAL_BITS        ; save the special bits seperate
Radio1P5R:
                ld      pointerh,#Radio1P5H     ; get the pointer
                ld      pointerl,#Radio1P5L     ;
                jr      AddAll
SPECIAL_BITS:
                cp      radioc,#15d             ; test for the first special
                jr      nz,SKIP_ID_ZERO         ; if not then skip zeroing
                clr     ID_B                    ; else clear the id bits
```

```
SKIP_ID_ZERO:
                cp      radioc,#19d             ; test for the switch id
                jr      z,SWITCHID              ; if so then branch

                ld      rtemph,ID_B             ; save the special bit
                add     ID_B,rtemph             ; *3
                add     ID_B,rtemph             ; *3
                add     ID_B,BIT1P5             ; add in the new value
                jr      Radio1P5R
SWITCHID:
                ld      SW_B,BIT1P5             ; save the switch ID
;               cp      ID_B,#03d               ; test for the add in values
;               jr      ule,Radio1P5R           ; add in if 3 <
;               clr     BIT1P5                  ; else dont add in
                jr      Radio1P5R

RCP5INC:
                tm      radioc,#00000001b       ; test for even odd number
                jr      z,COUNTP5INC            ; if odd number counter

RadioP5INC:                                     ; else radio
                ld      pointerh,#RadioP5H      ; get the pointer
                ld      pointerl,#RadioP5L      ;
                jr      AddAll

COUNT1P5INC:
                ld      pointerh,#COUNT1P5H     ; get the pointer
                ld      pointerl,#COUNT1P5L     ;
                jr      AddAll
COUNTP5INC:

                ld      pointerh,#COUNTP5H      ; get the pointers
                ld      pointerl,#COUNTP5L      ;
                jr      AddAll

AddAll:
                ld      rtemph,@pointerh        ; get the value
                ld      rtempl,@pointerl        ;
                ld      addvalueh,@pointerh     ; get the value
                ld      addvaluel,@pointerl     ;

                add     addvaluel,rtempl        ; add x2
                adc     addvalueh,rtemph        ;
                add     addvaluel,rtempl        ; add x3
                adc     addvalueh,rtemph        ;
                add     addvaluel,BIT1P5        ; add in new number
                adc     addvalueh,#00h          ;
                ld      @pointerh,addvalueh     ; save the value
                ld      @pointerl,addvaluel     ;
ALLADDED:
                inc     radioc                  ; increase the counter
TWENTY?:
                and     RFlag,#11011111B        ; clear the bit for 10 bits
                cp      radioc,#21D             ; test for 20
                jp      nz,RRETURN              ; if not then return
                tm      RFlag,#00010000B        ; test flag 20 bit code
```

```
                jr      nz,KNOWCODE             ; if the second 20 bits received
FIRST20:
                or      RFlag,#00010000B        ; set the flag
                clr     radioc                  ; clear the radio counter
                jp      RRETURN                 ; return
GOT20CODE:
                cp      ID_B,#07d               ; test for the don't use ones
                jp      uge,ClearRadio          ; clear don't use
                cp      ID_B,#04d               ; test for the don't add in ones
                jr      uge,KNOWCODE            ; if so then don't add in
                add     COUNT1P5L,SW_B          ; add in switch id
                adc     COUNT1P5H,#00h          ;
KNOWCODE:

;*****************************************************************************************************
; Translate the counter back to normal
;       start
;       CounterA        CounterB        CounterC        CounterD
;       00              00              Count1P5H       Count1P5L
;       MirrorA         MirrorB         MirrorC         MirrorD
;       00              00              CountP5H        CountP5L
;*****************************************************************************************************

                srp     #CounterGroup           ; set the group
                clr     countera                ; clear the counter Msb value
                clr     counterb                ;
                ld      counterc,COUNT1P5H      ; Set the value to count1p5
                ld      counterd,COUNT1P5L      ;
                clr     mirrora                 ; Set the mirror (temp reg for now)
                clr     mirrorb                 ; to countp5
                ld      mirrorc,COUNTP5H        ;
                ld      mirrord,COUNTP5L        ;
                call    AddMirrorToCounter      ; find countp5 * 3^10 + count1p5
                ld      loopcount,#3            ;
                call    RotateMirrorAdd         ;
                ld      loopcount,#2            ;
                call    RotateMirrorAdd         ;
                ld      loopcount,#2            ;
                call    RotateMirrorAdd         ;
                ld      loopcount,#2            ;
                call    RotateMirrorAdd         ;
                ld      loopcount,#1            ;
                call    RotateMirrorAdd         ;
                ld      loopcount,#3            ;
                call    RotateMirrorAdd         ;
                ld      loopcount,#1            ;
                call    RotateMirrorAdd         ;
                ld      loopcount,#1            ;
                call    RotateMirrorAdd         ;

MirrorTheCounter:
                call    MirrorCounter           ; mirror the counter
CounterCorrected:
                cp      SkipRadio,#0FFH         ; test for the skip radio flag
                jp      z,ClearRadio            ; if active do not test the cpde
                cp      LearnTimer,#0FFH        ; test for in learn mode
```

```
                jp      z,TESTCODE              ; if not in learn the test the code
STORECODE:
DCODESTORE:
                cp      PRadioA,radio1p5h       ; test all 8 memorys for a match
                jr      nz,PP_NOT_M_D           ; if no match skip
                cp      PRadioB,radio1p5l       ; test all 8 memorys for a match
                jr      nz,PP_NOT_M_D           ; if no match skip
                cp      PRadioC,radiop5h        ; test all 8 memorys for a match
                jr      nz,PP_NOT_M_D           ; if no match skip
                cp      PRadioD,radiop5l        ; test all 8 memorys for a match
                jr      nz,PP_NOT_M_D           ; if no match skip
                cp      PRadioE,MirrorA         ; test all 8 memorys for a match
                jr      nz,PP_NOT_M_D           ; if no match skip
                cp      PRadioF,MirrorB         ; test all 8 memorys for a match
                jr      nz,PP_NOT_M_D           ; if no match skip
                cp      PRadioG,MirrorC         ; test all 8 memorys for a match
                jr      nz,PP_NOT_M_D           ; if no match skip
                cp      PRadioH,MirrorD         ; test all 8 memorys for a match
                jr      nz,PP_NOT_M_D           ; if no match skip
MatchedForStore:
                srp     #LearnEeGroup
                call    TESTMATCH               ; test for a matching code
                cp      address,#0FFH           ; test for a match
                jr      nz,WRITEAGAIN           ; if so store AGAIN for counter
                ld      address,#1FH            ; set the address
                call    ReadMemory              ; read the value
                add     mtemph,#4d              ; find the next address
                cp      mtemph,#1CH             ; test for out of range
                jr      ult,GOTDADDRESS         ;
                clr     mtemph                  ;
GOTDADDRESS:
                ld      mtempl,mtemph           ;
                ld      address,#1FH            ; store the new address
                call    WRITEMEMORY             ;
                ld      address,mtemph          ; set the code address to write
                call    WRITE_D_CODE            ; output the D code
                jr      NOWRITESTORE            ; reset the learn mode

WRITEAGAIN:
                call    WRITE_D_CODE            ; output the D code

NOWRITESTORE:
                or      P2,#00000010B           ; turn off the LED for flashing
                ld      LearnTimer,#0FFH        ; turn off the learn mode
                clr     RadioTimeOut            ; disable command from learn
                jr      ClearRadio              ; set for the next code


PP_NOT_M_D:
                ld      PRadioA,radio1p5h       ; save the present into the past
                ld      PRadioB,radio1p5l       ; save the present into the past
                ld      PRadioC,radiop5h        ; save the present into the past
                ld      PRadioD,radiop5l        ; save the present into the past
                ld      PRadioE,MirrorA         ; transfer the value
                ld      PRadioF,MirrorB
```

```
                ld      PRadioG,MirrorC
                ld      PRadioH,MirrorD
                                                ; reset radio

;*****************************************************************
; Clear interrupt
;*****************************************************************
ClearRadio:
                tm      RFlag,#00000001B        ; test for receiving without error
                jr      z,SKIPiRTO              ; if flag not set then donot clear timer
                clr     RadioTimeOut            ; clear radio timer
SKIPiRTO:
                clr     RadioC                  ; clear the radio counter
                clr     RFlag                   ; clear the radio flags
RRETURN:
                pop     RP                      ; reset the RP
                iret                            ; return

;*****************************************************************************************************
; rotate mirror LoopCount * 2 then add
;*****************************************************************************************************
RotateMirrorAdd:

                rcf                             ; clear the carry
                rlc     mirrord                 ;
                rlc     mirrorc                 ;
                rlc     mirrorb                 ;
                rlc     mirrora                 ;
                djnz    loopcount,RotateMirrorAdd ; loop till done
;*****************************************************************************************************
; Add mirror to counter
;*****************************************************************************************************
AddMirrorToCounter:
                add     counterd,mirrord        ;
                adc     counterc,mirrorc        ;
                adc     counterb,mirrorb        ;
                adc     countera,mirrora        ;
                ret

;*****************************************************************************************************
; Add mirror to counter
;*****************************************************************************************************
MirrorCounter:
                ld      loopcount,#32d          ; set the number of bits
MirrorLoop:
                rrc     countera                ; move the bits
                rrc     counterb                ;
                rrc     counterc                ;
                rrc     counterd                ;
                rlc     mirrord                 ;
                rlc     mirrorc                 ;
                rlc     mirrorb                 ;
                rlc     mirrora                 ;
                djnz    loopcount,MirrorLoop    ; loop for all the bits
                ret
```

```
;*****************************************************************************
;       Test the radio code for matching
;*****************************************************************************
TESTCODE:
            and     P2,#11111101B           ; turn on the LED for flashing
            srp     #LearnEeGroup
            call    TESTMATCH               ; test the code for a match
            or      P2,#00000010B           ; turn off the LED for flashing
            cp      Address,#0FFH           ; test for no match
            jp      z,TEST_TC_SEC           ; if no match try touchcode and sec

D_CODE_MATCH:
            cp      RadioTimeOut,#0FFH      ; test for the timeout
            jr      z,NewCode               ; if timer inactive then look for a new
            cp      LastM1Match,Address     ; test for the same address as the past
            jr      nz,NewCode              ; if not then test for a new code
            clr     RadioTimeOut            ; reclear the timer
            jp      ClearRadio              ; and update the past
NewCode:
            srp     #CheckGroup             ; set the rp
            call    TESTCOUNTER             ; test the counter for in range
            cp      CMP,#00                 ; test for a matching value
            jp      z,ClearRadio            ; if the same then clear the radio
            cp      CMP,#0AAH               ; test for counter in range
            jr      z,GOT_D_CMD             ; got a command save radio counter
            cp      CMP,#07FH               ; test for outside of - window
            jr      z,UPDATE_PAST           ; if so skip resync
            cp      PAST_MATCH,Address      ; test for the same address as the past
            jr      nz,UPDATE_PAST          ; if not then update the past value
            ld      pradioa,MirrorA         ; transfer the value
            ld      pradiob,MirrorB
            ld      pradioc,MirrorC
            ld      pradiod,MirrorD
            sub     pradiod,pradioh
            sbc     pradioc,pradiog
            sbc     pradiob,pradiof
            sbc     pradioa,pradioe         ; find the difference
            cp      pradioa,#00             ; test for less then 4 away
            jr      nz,UPDATE_PAST          ; if not then update the past
            cp      pradiob,#00
            jr      nz,UPDATE_PAST          ; if not then update the past
            cp      pradioc,#00
            jr      nz,UPDATE_PAST          ; if not then update the past
            cp      pradiod,#00             ; test for the zero case
            jr      z,UPDATE_PAST           ;
            cp      pradiod,#04d
            jr      ugt,UPDATE_PAST         ; if not then update the past
GOT_D_CMD:
            call    STORE_D_COUNTER         ; save the new counter value

D_RADIO_COMMAND
            cp      SysDisable,#32d         ; test for 4 seconds
            jr      ult,TEST_TC_SEC         ; if not test tc and sec

            cp      RadioTimeOut,#RTOPERIOD ; test for first reception
```

```
                jr      ult,NOTP3A              ; if second reception skip t and mono
                clr     Mono                    ; clear the monostable
                or      P2,#00011000B           ; turn on the constant
                xor     P2,#01000000B           ; toggle the T output
NOTP3A:         clr     RadioTimeOut            ; clear the timer
NOTP3:
NOTP3S:
                jr      TEST_TC_SEC             ; test tc and sec

NOTNEWMATCH:
                ld      LearnTimer,#0FFH        ; set the learn timer "turn off"
                jp      ClearRadio              ; clear the radio

UPDATE_PAST:
                ld      PAST_MATCH,Address      ; save the past address
                ld      pradioe,MirrorA         ; transfer the value
                ld      pradiof,MirrorB
                ld      pradiog,MirrorC
                ld      pradioh,MirrorD
                jp      ClearRadio              ; reset the radio



;*******************************************************************************************
;       We know the code does not match but if it was our touch code
;       or security transmitter update the counter
;*******************************************************************************************
;
TEST_TC_SEC:
                srp     #LearnEeGroup
                cp      ID_B,#1d                ; test for the touch code
                jr      z,TC_SEC                ; jump if so
                cp      ID_B,#2d                ; test for the security transmitter
                jr      z,TC_SEC                ; jump if so
                jp      ClearRadio
TC_SEC:
                ld      address,#01d            ; set the start addresss for the fixed
NEXT_D:
                call    ReadMemory              ; read the word at this address
                cp      mtemph,Radio1P5H        ; test for the match
                jr      nz,NO_TC_MATCH          ; if not matching do the next address
                cp      mtempl,Radio1P5L        ; test for the match
                jr      nz,NO_TC_MATCH          ; if not matching do the next address
                dec     address                 ; reset the address
MatchedCheckCounter:
                call    TESTCOUNTER             ; test the counter for in range
                cp      CMP,#0AAH               ; test for within range
                jr      nz,SkipStoreCounter     ; if not kip storing the counter
TC_SEC_Store:
                call    STORE_D_COUNTER         ; save the new counter
SkipStoreCounter:
                inc     address
NO_TC_MATCH:
                add     address,#4d             ; set the address to the next code
                cp      address,#1CH            ; test for the last address
```

```
                jr      ult,NEXT_D                      ; if not the last address then try again

GOTNO_TC_MATCH:
                jp      ClearRadio

;*****************************************************************************************
;       Test the radio code counter and compares
;               CMP
;               00  => counter the same
;               FF => counter out of range
;               AA => counter in range
;               7F => counter within - window no resync
;               Address for test in address
;*****************************************************************************************

TESTCOUNTER:
                push    RP                      ; save the RP
                srp     #CheckGroup             ; set the rp
                inc     Address                 ; set the address to the 2x position for
                inc     Address                 ;
                call    ReadMemory              ; read the value
                ld      pradioa,MTempH          ; temp storage
                ld      pradiob,MTempL          ;
                inc     Address                 ;
                call    ReadMemory              ; read the value
                sub     Address,#3d             ; reset the address
                ld      pradioc,MTempH          ; temp storage
                ld      pradiod,MTempL          ;
                cp      MirrorA,pradioa         ; test first for the match
                jr      nz,NM_COUNTER           ; if not then test count position
                cp      MirrorB,pradiob         ;
                jr      nz,NM_COUNTER           ; if not then test count position
                cp      MirrorC,pradioc         ;
                jr      nz,NM_COUNTER           ; if not then test count position
                cp      MirrorD,pradiod         ;
                jr      nz,NM_COUNTER           ; if not then test count position
                ld      CMP,#00h                ; flag the match
CounterRet:
                pop     RP
                ret
NM_COUNTER:
                cp      pradioa,#0FFH           ; test for the roll over
                jr      nz,NORMALN              ; if not test normally
                cp      pradiob,#0FFH           ; test for the roll over
                jr      nz,NORMALN              ; if not test normally
                cp      MirrorA,#0H             ; test for the rollover
                jr      nz,NORMALN              ; if not test normally
                cp      MirrorB,#0H             ; test for the rollover
                jr      nz,NORMALN              ; if not test normally
                                                ; at roll com past add pres
                call    Complement              ;
                add     pradiod,MirrorD         ; add the 2
                adc     pradioc,MirrorC         ;
                adc     pradiob,MirrorB         ;
                adc     pradioa,MirrorA         ;
```

```
                cp      pradioc,#12d            ; window 3072 or 1024 activations
                jr      ule,COUNTOK
COUNTOUT:
                call    Complement              ; find the - difference
                cp      pradioa,#00             ; test for within 00000400H
                jr      nz,OutOfWindow          ;
                cp      pradiob,#00             ;
                jr      nz,OutOfWindow          ;
                cp      pradioc,#00000100B      ;
                jr      ugt,OutOfWindow         ;
                ld      CMP,#7FH                ; mark the -window function
                jr      CounterRet              ; return

OutOfWindow:
                ld      CMP,#0FFH               ; set the bad count flag
                jr      CounterRet              ; return
COUNTOK:
                ld      CMP,#0AAH               ; set the count flag ok
                jr      CounterRet              ; return
NORMALN:
                sub     pradiod,MirrorD         ; subtrace to find difference
                sbc     pradioc,MirrorC         ;
                sbc     pradiob,MirrorB         ;
                sbc     pradioa,MirrorA         ;
                call    Complement              ; make positive
                cp      pradioa,#00             ; test for to large
                jr      nz,COUNTOUT             ; if so out of window
                cp      pradiob,#00             ; test for to large
                jr      nz,COUNTOUT             ; if so out of window
                cp      pradioc,#11D            ; window for 1024
                jr      ule,COUNTOK             ;
                jr      COUNTOUT

Complement:
                com     pradiod                 ; Complement the temp reg
                com     pradioc                 ;
                com     pradiob                 ;
                com     pradioa                 ;
                ret

;*****************************************************************************************
;       TESTMATCH TEST THE NON ROLLING PART OF ANY CODE IF THERE
;       IS A MATCH RETURNS THE ADDRESS ELSE RETURNS FF
;*****************************************************************************************

TESTMATCH:

TEST_D_CODES:
                clr     address                 ; start at address 0
NEXT_D_CODE:
                call    ReadMemory              ; read the word at this address
                cp      mtemph,RadioP5H         ; test for the match
                jr      nz,NO_D_MATCH           ; if not matching then do next address
                cp      mtempl,RadioP5L         ; test for the match
                jr      nz,NO_D_MATCH           ; if not matching then do next address
```

```
                inc     address                 ; set the second half of the code
                call    ReadMemory              ; read the word at this address
                cp      mtemph,Radio1P5H        ; test for the match
                jr      nz,NO_D_MATCH2          ; if not matching do the next address
                cp      mtempl,Radio1P5L        ; test for the match
                jr      nz,NO_D_MATCH2          ; if not matching do the next address
                dec     address                 ; reset the address
                jr      TMEXIT                  ; return with the address of the match

NO_D_MATCH:
                inc     address                 ; set the address to the next code
NO_D_MATCH2:
                add     address,#3d             ; set the address to the next code
                cp      address,#1CH            ; test for the last address
                jr      ult,NEXT_D_CODE         ; if not the last address then try again

GOTNO_D_MATCH:
                ld      address,#0FFH           ; set the no match flag
                ret
TMEXIT:
                ld      LastM1Match,LastMatch   ; delay line
                ld      LastMatch,address       ; save the address for radio timeout
                ret


;*********************************************************************
; LEARN DEBOUNCES THE LEARN SWITCH 80mS
; TIMES OUT THE LEARN MODE 30 SECONDS
; DEBOUNCES THE LEARN SWITCH FOR ERASE 6 SECONDS
;*********************************************************************
LEARN:
                srp     #LearnModeGroup         ; set the group
                cp      cmdswitch,#236D         ; test for the debouncer release
                jr      nz,ReleaseDone          ; if not then test for set
                clr     cmdswitch               ; clear the debouncer
ReleaseDone:
                cp      cmdswitch,#20D          ; test for switch 2 set
                jr      UGT,CLEARRA             ;
multi2:
                cp      cmdswitch,#20D          ; test for switch 2 set
                jr      nz,TESTLEARN            ; if not then test learn
SW2isSET:

                ld      cmdswitch,#0FFH         ; set the debouncer
CMDSW:
                clr     mono                    ; clear the timer
                xor     P2,#01000000B           ; toggle
                or      P2,#00011000B           ; set
CLEARRA:
                clr     rto                     ;


TESTLEARN:
                cp      learndb,#236D           ; test for the debounced release
                jr      nz,LEARNNOTRELEASED     ; if  not released then jump
```

```
                clr     learndb                 ; clear the debouncer

                ret                             ; return

LEARNNOTRELEASED:
                cp      learnt,#0FFH            ; test for learn mode
                jr      nz,INLEARN              ; if in learn jump
                cp      learndb,#20D            ; test for debounce period
                jr      nz,ERASETEST            ; if not then test the erase period
SETLEARN:
                clr     learnt                  ; clear the learn timer
                ld      learndb,#0FFH           ; set the debouncer
                and     P2,#11111101b           ; turn on the led
ERASETEST:
                cp      learndb,#0FFH           ; test for learn button active
                jr      nz,ERASERELEASE         ; if button released set the erase timer
                cp      eraset,#0FFH            ; test for timer active
                jr      nz,ERASETIMING          ; if the timer active jump
                clr     eraset                  ; clear the erase timer
ERASETIMING:
                cp      eraset,#48D             ; test for the erase period
                jr      z,ERASETIME             ; if timed out the erase
                ret                             ; else we return
ERASETIME:
                or      P2,#00000010b           ; turn off the led
                ld      skipradio,#0FFH         ; set the flag to skip the radio read
                call    CLEARCODES              ; clear all codes in memory
                clr     skipradio               ; reset the flag to skip radio

                ld      learnt,#0FFH            ; set the learn timer
                ret                             ; return
ERASERELEASE:
                ld      eraset,#0FFH            ; turn off the erase timer
                ret                             ; return

INLEARN:
                cp      learndb,#20D            ; test for the debounce period
                jr      nz,TESTLEARNTIMER       ; if not then test the learn timer
                ld      learndb,#0FFH           ; set the learn db
TESTLEARNTIMER:
                cp      learnt,#240D            ; test for the learn 30 second timeout
                jr      nz,ERASETEST            ; if not then test erase
learnoff:
                or      P2,#00000010B           ; turn off the led
                ld      learnt,#0FFH            ; set the learn timer
                ld      learndb,#0FFH           ; set the learn debounce
                jr      ERASETEST               ; test the erase timer


;*****************************************************************
; WRITE WORD TO MEMORY
; ADDRESS IS SET IN REG ADDRESS
; DATA IS IN REG MTEMPH AND MTEMPL
; RETURN ADDRESS IS UNCHANGED
;*****************************************************************
```

```
WRITEMEMORY:
            push    RP                      ; SAVE THE RP
            srp     #LearnEeGroup           ; set the register pointer

            call    STARTB                  ; output the start bit
            ld      serial,#00110000B       ; set byte to enable write
            call    SERIALOUT               ; output the byte
            and     csport,#csl             ; reset the chip select
            call    STARTB                  ; output the start bit
            ld      serial,#01000000B       ; set the byte for write
            or      serial,address          ; or in the address
            call    SERIALOUT               ; output the byte
            ld      serial,mtemph           ; set the first byte to write
            call    SERIALOUT               ; output the byte
            ld      serial,mtempl           ; set the second byte to write
            call    SERIALOUT               ; output the byte
            call    ENDWRITE                ; wait for the ready status
            call    STARTB                  ; output the start bit
            ld      serial,#00000000B       ; set byte to disable write
            call    SERIALOUT               ; output the byte
            and     csport,#csl             ; reset the chip select
            pop     RP                      ; reset the RP
            ret

;*********************************************************************
; READ WORD FROM MEMORY
; ADDRESS IS SET IN REG ADDRESS
; DATA IS RETURNED IN REG MTEMPH AND MTEMPL
; ADDRESS IS UNCHANGED
;*********************************************************************
ReadMemory:
            push    RP                      ;
            srp     #LearnEeGroup           ; set the register pointer

            call    STARTB                  ; output the start bit
            ld      serial,#10000000B       ; preamble for read
            or      serial,address          ; or in the address
            call    SERIALOUT               ; output the byte
            call    SERIALIN                ; read the first byte
            ld      mtemph,serial           ; save the value in mtemph
            call    SERIALIN                ; read teh second byte
            ld      mtempl,serial           ; save the value in mtempl
            and     csport,#csl             ; reset the chip select
            pop     RP                      ;
            ret


;*********************************************************************
; WRITE D CODE TO 4 MEMORY ADDRESS
; CODE IS IN Radio1P5H Radio1P5L RadioP5H RadioP5L
; CODE IS IN Count1P5H Count1P5L CountP5H CountP5L
;*********************************************************************
WRITE_D_CODE:
            push    RP                      ;
            srp     #LearnEeGroup           ; set the register pointer
            ld      mtemph,RadioP5H         ; transfer the data
```

```
                ld      mtempl,RadioP5L         ;
                call    WRITEMEMORY             ; write the temp bits
                inc     address                 ; next address
                ld      mtemph,Radio1P5H        ; transfer the data
                ld      mtempl,Radio1P5L        ;
                call    WRITEMEMORY             ; write the temps
                inc     address                 ; next address
STORE_COUNTER:
                ld      mtemph,MirrorA          ; transfer the data
                ld      mtempl,MirrorB          ;
                call    WRITEMEMORY             ; write the temps
                inc     address                 ; next address
                ld      mtemph,MirrorC          ; transfer the data
                ld      mtempl,MirrorD          ;
                call    WRITEMEMORY             ; write the temps
                dec     address                 ; reset the address
                dec     address                 ;
                dec     address                 ;
                pop     RP                      ;
                ret                             ; return

STORE_D_COUNTER:
                push    RP                      ;
                srp     #LearnEeGroup           ; set the register pointer
                inc     address
                inc     address
                jr      STORE_COUNTER


;*****************************************************************
; START BIT FOR SERIAL NONVOL
; ALSO SETS DATA DIRECTION AND AND CS
;*****************************************************************
STARTB:
                ld      P2M,#P2M_INIT           ; set port 2 mode
                and     csport,#csl             ;
                and     clkport,#clockl         ; start by clearing the bits
                and     dioport,#dol            ;
                or      csport,#csh             ; set the chip select
                or      dioport,#doh            ; set the data out high
                or      clkport,#clockh         ; set the clock
                and     clkport,#clockl         ; reset the clock low
                and     dioport,#dol            ; set the data low
                ret                             ; return

;*****************************************************************
; END OF CODE WRITE
;*****************************************************************
ENDWRITE:
                ld      P2M,#(P2M_INIT+1)       ; set port 2 mode
                and     csport,#csl             ; reset the chip select
                nop                             ; delay
                or      csport,#csh             ; set the chip select
                WDT                             ; kick the dog
ENDWRITELOOP:
                ld      temph,dioport           ; read the port
```

```
                and     temph,#doh              ; mask
                jr      z,ENDWRITELOOP          ; if the bit is low then loop
                and     csport,#csl             ; reset the chip select
                ld      P2M,#P2M_INIT           ; set port 2 mode forcing output mode
                ret

;*********************************************************************
; SERIAL OUT
; OUTPUT THE BYTE IN SERIAL
;*********************************************************************
SERIALOUT:
                ld      P2M,#P2M_INIT           ; set port 2 mode
                ld      templ,#8H               ; set the count for eight bits
SERIALOUTLOOP:
                rlc     serial                  ; get the bit to output into the carry
                jr      nc,ZEROOUT              ; output a zero if no carry
ONEOUT:
                or      dioport,#doh            ; set the data out high
                or      clkport,#clockh         ; set the clock high
                and     clkport,#clockl         ; reset the clock low
                and     dioport,#dol            ; reset the data out low
                djnz    templ,SERIALOUTLOOP
                                                ; loop till done
                ret                             ; return
ZEROOUT:
                and     dioport,#dol            ; reset the data out low
                or      clkport,#clockh         ; set the clock high
                and     clkport,#clockl         ; reset the clock low
                and     dioport,#dol            ; reset the data out low
                djnz    templ,SERIALOUTLOOP
                                                ; loop till done
                ret                             ; return

;*********************************************************************
; SERIAL IN
; INPUTS A BYTE TO SERIAL
;*********************************************************************
SERIALIN:
                ld      P2M,#(P2M_INIT+1)       ; set port 2 mode
                ld      templ,#8H               ; set the count for eight bits
SERIALINLOOP:
                or      clkport,#clockh         ; set the clock high
                rcf                             ; reset the carry flag
                ld      temph,dioport           ; read the port
                and     temph,#doh              ; mask out the bits
                jr      z,DONTSET
                scf                             ; set the carry flag
DONTSET:
                rlc     serial                  ; get the bit into the byte
                and     clkport,#clockl         ; reset the clock low
                djnz    templ,SERIALINLOOP
                                                ; loop till done
                ret                             ; return
```

```
;*******************************************************************
; CLEAR PAGE 0 CODES IN THE MEMORY
;*******************************************************************
CLEARCODES:
            push    RP
            di                              ; disable interrupts
            ld      SkipRadio,#0FFH         ;
            srp     #LearnEeGroup           ; set the register pointer
            ld      Radio1P5H,#0FFH         ; set the codes to illegal codes
            ld      Radio1P5L,#0FFH         ;
            ld      RadioP5H,#0FFH          ;
            ld      RadioP5L,#0FFH          ;
            clr     address                 ; set the page
            ld      cmp,#07d                ; erase 7 values
ClearLoop:
            call    WRITE_D_CODE            ; clear this address
            add     address,#4d             ; next clear address
            djnz    cmp,ClearLoop           ;
            clr     mtemph                  ; clear data
            clr     mtempl
            ld      address,#1FH            ; set the address
            call    WRITEMEMORY             ;
            pop     RP                      ;
            ret                             ; return

;*******************************************************************
; TIMER UPDATE FROM INTERUPT EVERY .256mS
;*******************************************************************
TimerOneInt:
            inc     TaskSwitch              ; set to the next switch
            ld      IMR,#RETURN_IMR         ; turn on the interrupt
            tm      TaskSwitch,#00000001b   ; even odd
            jr      nz,SkipRsRoutine        ; do rs232 .5 mS
            call    RS232                   ; do the serial
SkipRsRoutine:
            tm      TaskSwitch,#00000011B   ; test for task 0,1,2 or 3
            jr      z,TASK1                 ; task 1 every 1 mS
TASK0:
            iret

TASK1:
            push    RP
ONEMS:
            srp     #LearnModeGroup         ; set the register pointer
            inc     T4MS                    ; increment the 4mS timer
            inc     T125MS                  ; increment the 125 mS timer
            cp      T4MS,#4D                ; test for the time out
            jp      nz,TEST125              ; if not true then jump
FOURMS:
            clr     T4MS                    ; reset the timer
            cp      rto,#0FFh               ; test for the end of the rto
            jr      z,RTOOK                 ; if the radio timeout ok then skip
            inc     rto                     ; increment the rto
RTOOK:
            ei                              ; enable the interrupts
```

```
                inc     mono                    ; increment the mono time out
                jr      nz,MONOOK               ; if the mono timeout ok then skip
                dec     mono                    ; back turn
MONOOK:                                         ;
                cp      SwitchSkip,#00          ; test for the skip switches command
                jr      nz,TEST125              ;

TESTSW1:
                tm      P2,#00100000B           ; test switch one
                jr      z,SW1SET                ; if set jump
                cp      LearnDebounce,#00H      ; test for min number
                jr      z,TESTSW2               ; if at min skip dec
                dec     LearnDebounce           ; dec debouncer down
                jr      TESTSW2                 ; next
SW1SET:
                cp      LearnDebounce,#0FFH     ; test for the max number
                jr      z,TESTSW2               ; if at max skip inc
                inc     LearnDebounce           ; inc the debouncer

TESTSW2:
                tm      P2,#00000100B           ; test switch two
                jr      z,SW2SET                ; if set jump
                cp      CmdSwitch,#00H          ; test for min number
                jr      z,TESTSWDB              ; if at min skip dec
                dec     CmdSwitch               ; dec debouncer down
                jr      TESTSWDB                ; next
SW2SET:
                cp      CmdSwitch,#0FFH         ; test for the max number
                jr      z,TESTSWDB              ; if at max skip inc
                inc     CmdSwitch               ; inc the debouncer

TESTSWDB:


TEST125:
                cp      T125MS,#125D            ; test for the time out
                jr      z,ONE25MS               ; if true the jump
                pop     RP
                iret
ONE25MS:
TOG:
                ei                              ; enable the interrupts
                clr     T125MS                  ; reset the timer
                cp      SysDisable,#0FFH        ; test for the top
                jr      z,DO12
                inc     SysDisable              ; count off the system disable timer
DO12:
                cp      learnt,#0FFH            ; test for overflow
                jr      z,LEARNTOK              ; at roll over  skip
                inc     learnt                  ; increase the learn timer
LEARNTOK:
                cp      eraset,#0FFH            ; test for overflow
                jr      z,ERASET1OK             ; if at roll skip
                inc     eraset                  ; increase the erase timer
ERASET1OK:
                pop     RP
```

```
                iret

;-------------------------------------------------------------------------
;       RS232 DATA ROUTINES
;-------------------------------------------------------------------------

;       enter rs232 start with word to output in rs232do

RS232OSTART:
                push    rp                      ; save the rp
                srp     #TimerGroup             ; set the group pointer
                clr     RSStart                 ; one shot
                ld      rs232odelay,#6d         ; set the time delay to 3. mS
                clr     rs232docount            ; start with the counter at 0
                and     RS232OP,#RS232OC        ; clear the output
                jr      NORSOUT                 ;


RS232:
                cp      RSStart,#0FFH           ; test for the start flag
                jr      z,RS232OSTART
RS232OUTPUT:
                push    rp                      ; save the rp
                srp     #TimerGroup             ; set the group pointer
                cp      rs232docount,#11d       ; test for last
                jr      nz,RS232R
                or      RS232OP,#RS232OS        ; set the output idle
                JR      NORSOUT
RS232R:
                djnz    rs232odelay,NORSOUT     ; cycle count time delay
                inc     rs232docount            ; set the count for the next cycle
                scf                             ; set the carry flag for stop bits
                rrc     rs232do                 ; get the data into the carry
                jr      c,RS232SET              ; if the bit is high then set
                and     RS232OP,#RS232OC        ; clear the output
                jr      SETTIME                 ; find the delay time
RS232SET:
                or      RS232OP,#RS232OS        ; set the output
SETTIME:
                ld      rs232odelay,#6d         ; set the data output delay
                tm      rs232docount,#00000001b ; test for odd words
                jr      z,NORSOUT               ; if even done
                ld      rs232odelay,#7d         ; set the delay to 7 for odd
                                                ; this gives 6.5 *.512mS

NORSOUT:
RS232INPUT:
                cp      rs232dicount,#0FFH      ; test  mode
                jr      nz,RECEIVING            ; if receiving then jump
                tm      RS232IP,#RS232IM        ; test the incoming data
                jr      nz,NORSIN               ; if the line is still idle then skip
                clr     rs232dicount            ; start at 0
                ld      rs232idelay,#3          ; set the delay to mid
RECEIVING:
                djnz    rs232idelay,NORSIN      ; skip till delay is up
```

```
                inc     rs232dicount                ; bit counter
                cp      rs232dicount,#10d           ; test for last timeout
                jr      z,DIEVEN
                tm      RS232IP,#RS232IM            ; test the incoming data
                rcf                                 ; clear the carry
                jr      z,SKIPSETTING               ; if input bit not set skip setting carry
                scf                                 ; set the carry
SKIPSETTING:
                rrc     rs232di                     ; save the data into the memory
                ld      rs232idelay,#6d             ; set the delay
                tm      rs232dicount,#00000001b     ; test for odd
                jr      z,NORSIN                    ; if even skip
                ld      rs232idelay,#7              ; set the delay
                jr      NORSIN
DIEVEN:
                ld      rs232dicount,#0FFH          ; turn off the input till next start
                ld      rscommand,rs232di           ; save the value
                clr     RSCount                     ; clear the counter
NORSIN:
                pop     rp                          ; return the rp
                ret

                Fill
                Fill
                Fill
                Fill
                Fill
                Fill
                Fill

.end
```

United States Patent & Trademark Office

Office of Initial Patent Examination -- Scanning Division



Application deficiencies found during scanning:

☑ Page(s) ~~X~~ A-97 of Miscellaneous was ~~were~~ not present for scanning.
(Document title)

☐ Page(s)_____ of_____ were not present for scanning.
(Document title)

☐ ***Scanned copy is best available.***